

## Errata

**Title & Document Type:** 5216A Electronic Counters Operating and Service Manual

**Manual Part Number:** 05216-9006

**Revision Date:** August 1971

### About this Manual

We've added this manual to the Agilent website in an effort to help you support your product. This manual provides the best information we could find. It may be incomplete or contain dated information, and the scan quality may not be ideal. If we find a better copy in the future, we will add it to the Agilent website.

### HP References in this Manual

This manual may contain references to HP or Hewlett-Packard. Please note that Hewlett-Packard's former test and measurement, life sciences, and chemical analysis businesses are now part of Agilent Technologies. The HP XXXX referred to in this document is now the Agilent XXXX. For example, model number HP8648A is now model number Agilent 8648A. We have made no changes to this manual copy.

### Support for Your Product

Agilent no longer sells or supports this product. You will find any other available product information on the Agilent Test & Measurement website:

[www.agilent.com](http://www.agilent.com)

Search for the model number of this product, and the resulting product page will guide you to any available information. Our service centers may be able to perform calibration if no repair parts are needed, but no other support from Agilent is available.




**Agilent Technologies**

## OPERATING AND SERVICE MANUAL

# ELECTRONIC COUNTER

## 5216A

HEWLETT **hp** PACKARD

# **ELECTRONIC COUNTER**

## **5216A**

**H/P Part No. 05216-9006**

### **SERIAL PREFIX: 1040A**

This manual applies directly to HP Model 5216A Electronic Counters having serial prefix number 1040A.

### **SERIAL PREFIXES NOT LISTED**

For serial prefixes above 1040A, a "Manual Changes" sheet is included with this manual. For serial prefixes below 1040A, refer to Section VII, Manual Changes.

Copyright HEWLETT-PACKARD COMPANY 1968  
5301 STEVENS CREEK BLVD., SANTA CLARA, CALIF. 95050

**02430-3**

**Printed: AUG 1971**

**HEWLETT  PACKARD**

4-18"  
49

## MANUAL CONTENT

This manual is supplied to help you make best use of your instrument. The manual covers 8 sections of information as follows:

Section I is an introduction to the instrument. Electrical specifications are given, plus information on accessories.

Section II covers inspection, power, mounting, packing, shipping and connection.

Section III outlines operating procedures.

Section IV discusses technical details of circuit operation.

Section V provides performance check, troubleshooting and adjustment procedures.

Section VI lists replaceable parts.

Section VII gives information on manual changes.

Section VIII contains circuit diagrams with component location.

## HOW TO ORDER

To order an operating and service manual, contact your nearest Hewlett-Packard Sales and Service office. Give complete model, name and 8- or 9-digit serial number. The serial number plate is on the rear panel (see Paragraph 1-7 for serial number system). Comments on this manual are welcome at any Sales and Service Office.

## TABLE OF CONTENTS

Section		Page
I	GENERAL INFORMATION . . . . .	1-1
	1-1. Introduction . . . . .	1-1
	1-3. Equipment Supplied . . . . .	1-1
	1-5. Accessories Available . . . . .	1-1
	1-7. Instrument Identification . . . . .	1-1
II	INSTALLATION . . . . .	2-1
	2-1. Unpacking and Inspection . . . . .	2-1
	2-3. Storage and Shipment . . . . .	2-1
	2-8. Rack Insulation . . . . .	2-1
	2-12. Filler Panels . . . . .	2-1
	2-14. Operation from 115 or 230 Vac . . . . .	2-1
III	OPERATION . . . . .	3-1
	3-1. Introduction . . . . .	3-1
	3-3. Controls . . . . .	3-1
	3-11. Digital Recorder Output . . . . .	3-1
IV	THEORY OF OPERATION . . . . .	4-1
	4-1. Introduction . . . . .	4-1
	4-3. Blanking . . . . .	4-1
	4-5. Gating and Logic . . . . .	4-1
	4-7. Logic Symbols . . . . .	4-1
	4-10. Multiple Input JK Flip-Flop . . . . .	4-2
	4-12. JK Master-Slave Flip-Flop . . . . .	4-2
	4-14. Input Attenuator Assembly A1 . . . . .	4-2
	4-16. Input Amplifier Assembly A2 . . . . .	4-2
	4-18. 1 MHz Oscillator Assembly A3 . . . . .	4-3
	4-20. Main Board Assembly A4 . . . . .	4-3
	4-22. A4 Main Board . . . . .	4-3
	4-45. Decimal Point and Measurement Unit Assembly A5 . . . . .	4-4
	4-47. Power Supply Assembly A6 . . . . .	4-4
V	MAINTENANCE . . . . .	5-1
	5-1. Introduction . . . . .	5-1
	5-3. Assembly Designations . . . . .	5-1
	5-5. Test Equipment . . . . .	5-1
	5-7. Instrument Cover Removal . . . . .	5-1
	5-9. In-Cabinet Performance Check . . . . .	5-1
	5-11. Troubleshooting . . . . .	5-2
	5-12. General . . . . .	5-2
	5-14. Removal of Main Board Assembly A4 . . . . .	5-2
	5-16. Substitution . . . . .	5-12
	5-18. Printed Circuit Component Replacement . . . . .	5-12
	5-20. Adjustments . . . . .	5-12
	5-22. Power Supply Assembly A6 . . . . .	5-12
	5-24. 1 MHz Oscillator Assembly A3 . . . . .	5-12
VI	REPLACEABLE PARTS . . . . .	6-1
	6-1. Introduction . . . . .	6-1
	6-4. Ordering Information . . . . .	6-1
VII	MANUAL CHANGES . . . . .	7-1
	7-1. Current Instruments . . . . .	7-1
	7-3. Newer Instruments . . . . .	7-1
	7-5. Older Instruments . . . . .	7-1
VII	CIRCUIT DIAGRAMS . . . . .	8-1
	8-1. Introduction . . . . .	8-1


## LIST OF FIGURES

Figure		Page
1-1.	Model 5216A And Accessories . . . . .	1-0
2-1.	Adapter Frame and Combining Case . . . . .	2-2
3-1.	Front Panel Controls and Connectors . . . . .	3-2
3-2.	Rear Panel Controls and Connectors . . . . .	3-3
3-3.	Self Check . . . . .	3-4
3-4.	Frequency Measurements . . . . .	3-5
3-5.	Period Measurements . . . . .	3-6
3-6.	Totalizing Operation . . . . .	3-7
3-7.	Ratio Measurements . . . . .	3-8
3-8.	Time Interval Measurements . . . . .	3-9
4-1.	Gate Symbols . . . . .	4-1
4-2.	Logic Function Comparison . . . . .	4-1
4-3.	Multiple Input JK Flip-Flop . . . . .	4-2
4-4.	JK Flip-Flop . . . . .	4-2
5-1.	Test Setup for Time Interval Checks . . . . .	5-3
5-2.	Bottom and Sides Internal Views . . . . .	5-9
5-3.	Oscillator Frequency Test Setup . . . . .	5-12
6-1.	Cabinet Parts . . . . .	6-2
7-1.	A1 Input Attenuator (Component Locator) (Sheet 1 of 2) . . . . .	7-8
	A1 Input Attenuator (Schematic) (Sheet 2 of 2) . . . . .	7-9
7-2.	A4 Main Board (Schematic) (Sheet 1 of 3) . . . . .	7-11
7-3.	A4 Main Board (Schematic) (Sheet 2 of 3) . . . . .	7-12
7-4.	A4 Main Board (Schematic) (Sheet 3 of 3) . . . . .	7-13
7-5.	A6 Power Supply (Component Locator) (Sheet 1 of 2) . . . . .	7-14
	A6 Power Supply (Schematic) (Sheet 2 of 2) . . . . .	7-15
7-6.	A4 Main Board (Component Locator) . . . . .	7-16
7-7.	A4 Main Board (Schematic) (Sheet 2 of 3) . . . . .	7-17
7-8.	A4 Main Board (Component Locator) . . . . .	7-18
7-9.	A4 Main Board (Schematic) (Sheet 1 of 3) . . . . .	7-19
7-10.	A4 Main Board (Schematic) (Sheet 2 of 3) . . . . .	7-20
7-11.	A4 Main Board (Schematic) (Sheet 3 of 3) . . . . .	7-21
7-12.	A3 10 MHz Oscillator, A5 Decimal Point and Measurement Unit (Component Locator) (Sheet 1 of 2) . . . . .	7-22
7-13.	A3 10 MHz Oscillator, A5 Decimal Point and Measurement Unit (Schematic) (Sheet 2 of 2) . . . . .	7-23
8-1.	Schematic Diagram Notes . . . . .	8-2
8-2.	Integrated Circuit Diagrams . . . . .	8-3
8-3.	Flow Diagram for Frequency Measurements . . . . .	8-7
8-4.	Flow Diagram for Period Measurements . . . . .	8-9
8-5.	Flow Diagram for Ratio Measurements . . . . .	8-11
8-6.	Flow Diagram for Time Interval Measurements . . . . .	8-13
8-7.	A1 Input Attenuator . . . . .	8-15
8-8.	A2 Input Amplifier . . . . .	8-17
8-9.	A3 10 MHz Oscillator, A5 Decimal Point and Measurement Unit . . . . .	8-19
8-10.	A4 Main Board (Sheet 1 of 3) . . . . .	8-21
	A4 Main Board (Sheet 2 of 3) . . . . .	8-23
	A4 Main Board (Sheet 3 of 3) . . . . .	8-25
8-11.	A6 Power Supply . . . . .	8-27

## LIST OF TABLES

Table		Page
1-1.	Equipment Supplied . . . . .	1-1
1-2.	Accessories Furnished . . . . .	1-1
1-3.	Model 5216A Specifications . . . . .	1-2
2-1.	Filler Panels Available . . . . .	2-1
3-1.	Digital Recorder Jack Pin Connections . . . . .	3-1
4-1.	Truth Table . . . . .	4-2
5-1.	Assembly Identification . . . . .	5-1
5-2.	Recommended Test Equipment . . . . .	5-1
5-3.	In-Cabinet Performance Check . . . . .	5-2
5-4.	Front Panel Troubleshooting Check . . . . .	5-10
5-5.	Function Switch Connections to Main Board A4 . . . . .	5-12
6-1.	Reference Designation Index . . . . .	6-2
6-2.	Replaceable Parts . . . . .	6-7
6-3.	Code List of Manufacturers . . . . .	6-9
7-1.	Manual Changes . . . . .	7-2
7-2.	A4-05216-6011 Main Board Parts . . . . .	7-5
7-3.	A6-05216-6002 Power Supply Parts . . . . .	7-7
7-4.	A3-05216-6006 Oscillator Parts . . . . .	7-7

Figure 1-1. Model 5216A and Accessories





## SECTION I

### GENERAL INFORMATION

#### 1-1. INTRODUCTION

1-2. The Hewlett-Packard Model 5216A is a 12.5 MHz Electronic Counter that makes frequency measurements, period measurements, period average measurements, ratio measurements, totalizing and time interval measurements. All electrical and mechanical specifications are given in Table 1-3. The HP Model 5216A provides these additional features:

- a. Standard output frequency of 1 MHz.
- b. Display storage permits readings to be displayed while new count is being made.
- c. Blanking feature suppresses the display of unwanted zeros when storage is on.
- d. Seven digit display using digital display tubes; decimal point position and measurement units displayed automatically.
- e. Four-line BCD code output of 1248 "1" state positive provided for use with digital recorder.
- f. Remote reset control is available through rear panel BNC with contact closure to ground.

#### 1-3. EQUIPMENT SUPPLIED

1-4. Equipment supplied with the Model 5216A is listed in Table 1-1.

#### 1-5. ACCESSORIES AVAILABLE

1-6. Accessories available for the Model 5216A are listed in Table 1-2.

#### 1-7. IDENTIFICATION

1-8. Hewlett-Packard uses a two-section serial number mounted on the rear panel. Earlier instruments use an 8-digit serial number (000-00000). The first three digits are a serial prefix number; the last five digits refer to the specific instrument. Later instruments use a 9-digit serial number (0000A00000). The first four digits are the serial prefix and the last five digits refer to the specific instrument.

1-9. If the serial prefix of your instrument differs from that listed on the title page of this manual, there are differences between this manual and your instrument. Lower serial prefixes are documented in Section VII, and higher serial prefixes are covered with manual change sheets included with the manual. If the change sheet is missing, contact the nearest Hewlett-Packard Sales and Service Office listed on the inside rear cover of this manual.

Table 1-1. Equipment Supplied

Description	HP Part No.
Detachable power cord: 7-1/2 feet (231 cm) long, NEMA plug	820-1348
Cable: 4 feet (122 cm) long, male BNC connectors	10503A

Table 1-2. Accessories Available

Description	HP Part No.
Digital Recorder	5050A
Recorder Interconnecting cable	10513A
Rack Mount Adapter Frame	5060-0797
Combining Case	1052A

Table 1-3. Model 5216A Specifications

### FREQUENCY MEASUREMENT

Range: 3 Hz to 12.5 MHz.

Input: 10 mV rms sine wave, max. sensitivity.  
Approx. 1 M $\Omega$  shunted by 50 pF input impedance.

Gate Times: 10, 1, 0.1, 0.01 s.

Accuracy:  $\pm 1$  count  $\pm$  time base accuracy.

Readout: 7 long-life Nixies<sup>®</sup>, reads in MHz and kHz with positioned decimal point.

### TIME INTERVAL MEASUREMENT

Range: 10 ns to 10 s.

Input: Contact closure or saturated NPN transistor to ground. Signal duration  $\geq 1 \mu$ s. Current sinking  $\geq 2$  mA. The START signal must end before the STOP signal begins. Time from STOP to next START:  $\geq 30$  ms for external reset or  $\geq 30$  ms plus sample time for internal reset.

Frequency Counted: 1 MHz internal time base or external frequency standard.

Readout: ms with positioned decimal point.

### PERIOD MEASUREMENT

Range: 3 Hz to 1 MHz single period; to 2 MHz in multiple periods averaged.

Periods Averaged: 1, 10, 10<sup>2</sup>, 10<sup>3</sup>, 10<sup>4</sup>, 10<sup>5</sup>.

Input: 10 mV rms maximum sensitivity; 100 mV rms below 1 kHz.

Frequency Counted: 1 MHz internal time base or external frequency standard.

Accuracy:  $\pm 1$  count  $\pm$  time base accuracy  $\pm$  trigger error\*.

Readout: ms and  $\mu$ s with positioned decimal point.

### RATIO MEASUREMENT

Displays:  $(f_1/f_2) \times$  period multiplier<sup>\*</sup>; multipliers: 1, 10, 10<sup>2</sup>, 10<sup>3</sup>, 10<sup>4</sup>, 10<sup>5</sup>.

Range, Sensitivity:  $f_1$ : 1 kHz to 2 MHz into external time base BNC connector, 1V rms min. into 1000 $\Omega$ .  
 $f_2$ : 3 Hz to 1 MHz single period, to 2 MHz in multiple periods averaged, 10 mV rms sensitivity except 100 mV rms below 1 kHz.

Accuracy:  $\pm 1$  count of  $f_1$   $\pm$  trigger error of  $f_2$  \*.

### TIME BASE

Crystal Frequency: 1 MHz.

Stability: Aging Rate: less than  $\pm 1 \times 10^{-6}$ /month.  
Temperature: less than  $\pm 5 \times 10^{-6}$  from +10°C to +40°C; less than  $\pm 3 \times 10^{-5}$  from 0°C to +50°C.  
Line Voltage: less than  $1 \times 10^{-6}$  for  $\pm 10\%$  change.

Output Frequency: 1 MHz, 3V p-p min. open circuit; source impedance is 2000 ohm maximum.

External Std Input: 1 kHz to 2 MHz sine wave, 1V rms into 1000 ohm (10V rms maximum).

### GENERAL

Display: 7 digits, long-life Nixies<sup>®</sup>

Display Storage, Blanking: Yes

Sample Rate: 50ms to 5s or hold until manual reset.

Reset: Manual by pushbutton or remote, activated by contact closure or saturated NPN transistor to ground on rear panel BNC connector.

Signal Input:

Sensitivity: 10 mV rms sine wave, maximum sensitivity; 30 mV peak pulse, minimum pulse width 40 ns.

Impedance: Approx. 1 M $\Omega$  shunted by 50 pF.

Attenuation: Step attenuator, 0.01, 0.1, 1, 10V settings.

Trigger Level Adjustment: Continuously variable trigger level control.

Overload: Input voltage should not exceed 60 dB above attenuator setting or 300V rms (damage level).

Self Check: Works on all functions.

Digital Output:

Code: 1248 "1" state positive; "0" level: 0V nominal; "1" level: +5V open circuit, nominal; source impedance: 7.5K $\Omega$  max. each line.

Reference Levels: Ground; +5V, low impedance.

Print Command: Step from 0V to +5V dc coupled.

Hold-off Requirements: Voltage must be between -10V and -15V.

Chassis Connector: Accepts HP Cable 10513A with one special connector for the 5216A and one 50-pin Amphenol or Cinch type 57-30500-375, HP Part No. 1251-0086, male connector for HP 562A 5050A or 5055A Digital Recorders.

Operating Temperature Range: 0°C to +50°C.

Power Requirements: 115/230V  $\pm 10\%$ , 50 to 400 Hz, 20W maximum.

Weight: Net 7 lbs (3,1 kg); shipping 8-1/2 lbs (3,9 kg).

Accessories Furnished: HP 10503A, 4 feet, 50 $\Omega$  cable, BNC connectors. Detachable power cord, 7-1/2 feet (231 cm) long, NEMA plug.

Dimensions:



\* Trigger error for 10 mV rms sine wave input is less than  $\pm 0.3\%$  of one period periods averaged for signals with 40 dB signal-to-noise ratio. Decreases with increased signal amplitude and slope.

©Burroughs Corporation

## SECTION II

### INSTALLATION

#### 2-1. UNPACKING AND INSPECTION

2-2. If the shipping carton is damaged, ask that the carrier's agent be present when the instrument is unpacked. Inspect the instrument for damage (dents, scratches, broken knobs, etc.). If the instrument is damaged or fails to meet specifications, (Performance Check, Paragraph 5-9), notify the carrier and the nearest Hewlett-Packard Sales and Service office immediately (offices are listed at the back of this manual). Retain the shipping carton and the padding material for the carrier's inspection. The Sales and Service office will arrange for the repair or replacement of the instrument without waiting for the claim against the carrier to be settled.

#### 2-3. STORAGE AND SHIPMENT

2-4. To protect valuable electronic equipment during storage or shipment always use the best packing methods available. Your Hewlett-Packard Sales and Service office can provide packing material such as that used for original factory packaging. Contract packaging companies in many cities can provide dependable custom packaging on short notice. Here are two recommended packaging methods:

2-5. **RUBBERIZED HAIR.** Cover painted surfaces of instrument with protective wrapping paper. Pack instrument securely in strong corrugated container (350 lb/sq. in. bursting test) with 2-inch rubberized hair pads placed along all surfaces of instrument. Insert fillers between pads and container to ensure a firm fit.

2-6. **EXCELSIOR.** Cover painted surfaces of instrument with protective wrapping paper. Pack instrument in strong corrugated container (350 lb/sq. in. bursting test) with a layer of excelsior about 6 inches thick packed firmly against all surfaces of instrument.

2-7. **ENVIRONMENT.** Conditions during storage and shipment should be limited as follows:

- a. Maximum temperature: +167°F (+75°C).
- b. Minimum temperature: -40°F (-40°C).

#### 2-8. RACK INSTALLATION

2-9. When instrument is to be rack-mounted, a combining case (Paragraph 2-10) or adapter frame (Paragraph 2-11) is required. These items are available through the Hewlett-Packard Sales and Service offices. The following two paragraphs outline the two methods for rack-mounting the instrument.

2-10. **COMBINING CASE.** The combining case (HP 1052A) shown in Figure 2-1 is a unit which accepts two instruments of 5216A size. The combining case can be used as a bench model or it can be rack mounted. A rack mounting kit (HP Part No. 5060-0777) is supplied with the combining case. Instructions for using the

case are given in Figure 2-1. When only half the case is used, a blank filler panel (HP Part No. 5060-0794) is available to enclose the unused half.

2-11. **ADAPTER FRAME.** The adapter frame (HP Part No. 5060-0797) in Figure 2-1 is a rack frame that accepts two units of 5216 size. It can only be rack mounted. Install instruments in the adapter frame as follows:

- a. Place adapter frame on edge of bench as shown in step 1 of Figure 2-1.
- b. Stack units in frame as shown in step 2. Place spacer clamp between units, step 3.
- c. Place two end spacer clamps (step 4) and push units into frame.
- d. Insert screws on either side of frame, step 5, and tighten until units are tight in frame. The complete assembly is now ready for rack mounting.

#### 2-12. FILLER PANELS

2-13. When only a portion of a combining case or adapter frame is used, blank filler panels are available to enclose the unused portion. Table 2-1 outlines filler panels available.

Table 2-1. Filler Panels Available

Dimensions	HP Part No.
6-3/32" high, 2-31/64" wide	5060-0795
6-3/32" high, 5-1/8" wide	5060-0793
6-3/32" high, 7-25/32" wide	5060-0794
3-1/32" high, 7-25/32" wide	5060-0097

#### 2-14. OPERATION FROM 115 OR 230 VAC

2-15. **GENERAL.** The instrument can be operated from either 115 or 230 Vac ( $\pm 10\%$ , 50 to 400 Hz) power lines. A rear panel slide switch permits operation from either voltage. Insert a narrow blade screwdriver in the switch slot and slide the switch to expose "115" marking for 115 volt operation or "230" marking for 230 volt operation. The ac line fuse is 0.3 for 115V and 0.15 for 230V operation.

2-16. **POWER CONNECTION.** The instrument is supplied with a detachable 3-wire power cable. Install as follows:

- a. Connect flat plug (3-conductor female connector) to the ac line jack at the rear of the instrument.
- b. Connect plug (2-blade male with round grounding pin) to 3-wire grounded ac outlet. Exposed portions of the instrument are grounded through the round pin on the plug for safety. When only a 2-blade outlet is available, use HP adapter 1251-0048 and connect short wire from side of adapter to ground.

Figure 2-1. Adapter Frame and Combining Case

**RACK ADAPTER FRAME**

**ALTERNATE COMBINATIONS**

**COMBINING CASE**

**ALTERNATE COMBINATIONS**

**STEP 1**  
SLIDE TOP PART TO LIMIT

**STEP 2**  
SLIDE BOTTOM PART TO LIMIT

**STEP 3**  
PUSH IN TO LIMIT

**STEP 4**  
SLIDE OVER TO LIMIT

**STEP 5**  
PUSH DOWN TO RELEASE

**STEP 6**  
PLACE INSTRUMENT INTO CASE

**STEP 7**  
SET RETAINER BACK INTO PLACE

**STEP 8**  
PUSH UP TO LOCK

ONE HALF MODULE SHOWN FOR TYPICAL INSTALLATION

**OPERATION**

## SECTION III

### OPERATION

#### 3-1. INTRODUCTION

3-2. The HP Model 5216A measures frequency, period average, ratio of two frequencies, and total events. A switch selects both measurement functions and time base or multiplier. A SENSITIVITY switch adjusts instrument sensitivity, the SAMPLE RATE control sets the measurement cycle rate.

#### 3-3. CONTROLS

3-4. Function Selector. This 12 position switch selects both measurement function and time base (gate time) or multiplier desired for the measurement.

3-5. SENSITIVITY Control. Adjusts instrument sensitivity. With proper settings, the counter will operate with input signals of .01 V rms (sine wave). A LEVEL control is incorporated in the SENSITIVITY switch. It provides trigger level adjustment for pulse input signals.

3-6. SAMPLE RATE Control. Sets the period of time following the gate closure until the gate may be opened again. With the counter in FREQUENCY mode, SAMPLE RATE is adjustable from approximately 0.05 sec (minimum) to at least 5 sec (maximum) and is independent of gate time. The HOLD position sets the display indefinitely.

3-7. RESET Pushbutton. When depressed, resets the display and internal count to zero. The counter after reset is ready to begin a new counting cycle.

3-8. STORAGE Switch. Disables the storage feature and controls zero blanking. The display storage feature provides a continuous visual display while the instrument is totalizing a new count. Only if the new count differs from the previous count will the display change. With storage on, a low level sets selected decades to zero at reset.

3-9. FREQ STD Switch. When this rear panel switch is set to INT, 1 MHz signal of the internal oscillator is available from the FREQ STD connector. When using an external frequency standard (or the higher of two frequencies for ratio measurement), set FREQ STD switch to EXT, and connect the external standard (or higher frequency signal) to FREQ STD connector.

3-10. FREQ-PER/TIME INT Switch. In FREQUENCY, PERIOD, or MANUAL, the switch should be in FREQ-PER position. To make time interval measurements, set switch to TIME INT. Connect start and stop control signals to START and STOP connectors on rear panel.

#### 3-11. DIGITAL RECORDER OUTPUT


3-12. To supply counter display information to the HP Model 5050A Printer, use digital recorder inter-

connecting cable HP Part No. 10513A. The DIGITAL RECORDER Jack will mate with 36-pin printed circuit connector A4J1 on the counter rear panel. Signals available and external signals required are given in Table 3-1. BCD output code is 1248, "1" state positive.

Table 3-1. Digital Recorder Jack Pin Connections

Function		A4J1 Pin No.
Display	Weight	
(Right End) $10^0$ Units	1	17
	2	16
	4	15
	8	18
$10^1$ Tens	1	6
	2	7
	4	8
	8	5
$10^2$ Hundreds	1	F
	2	H
	4	J
	8	E
$10^3$ Thousands	1	R
	2	N
	4	M
	8	P
$10^4$ Ten Thousands	1	L
	2	9
	4	10
	8	K
$10^5$ Hundred Thousands	1	11
	2	13
	4	14
	8	12
$10^6$ Millions	1	S
	2	V
	4	U
	8	T
Print Command output; 0V to +5V step, dc coupled.		4
Inhibit signal input; must be between -10V and -15V.		2
+5Volts positive reference, indicates "1" level for BCD output.		3
Ground		1

Figure 3-1, Front Panel Controls and Connector




1. INPUT jack couples input signal to input attenuator.
2. SENSITIVITY
  - a. Connects CHECK signal or attenuated input signal to input amplifier.
  - b. LEVEL control adjusts input trigger level.
3. Function - Time Base switch - selects multiplier for PERIODS AVERAGED measurements,

selects gate times for FREQUENCY measurements, and controls START and STOP for totalizing measurements.

4. SAMPLE RATE control turns counter on, holds display, and varies sample rate from 50 ms to 5 seconds.
5. RESET switch manually resets counter.
6. GATE light indicates gate open when light is on.


Figure 3-2. Rear Panel Controls and Connectors



1. DIGITAL RECORDER jack supplies BCD information to printer (see page 3-1).
2. AC LINE connector connects to flat plug on power cable.
3. Fuse provides overload protection.
4. Line Voltage switch selects either 115 or 230 Vac line; insert narrow blade and slide to right for 115V, slide to left for 230V.
5. STORAGE switch disables storage feature and controls zero blanking.
6. RESET jack provides remote reset of counter by contact closure to ground.
7. FREQ STD switch selects internal oscillator or external frequency standard.
8. FREQ STD jack provides 1 MHz output when internal oscillator is used; is input jack for 1 MHz external frequency standard.
9. FREQ-PER/TIME INT switch selects type of measurement, FREQ-PER or TIME INT.
10. START and STOP jacks control signal inputs for time interval measurements.
11. INPUT jack connected in parallel with front panel input jack.




Figure 3-3, Self Check



1. Set SAMPLE RATE control slightly clockwise out of POWER OFF.
2. Set SENSITIVITY switch to CHECK.
3. Set function selector to 1 PERIOD.
4. Set STORAGE switch to STORAGE.
5. Set FREQ STD switch to INT.
6. Adjust LEVEL control for stable count.


Position	Display
1 period	.001 ms
10 periods	.0010 ms
100 periods	.00100 ms
1K periods	1.000 $\mu$ s
10K periods	1.0000 $\mu$ s
100K periods	1.00000 $\mu$ s
0.01 sec	1.0000 MHz
0.1 sec	1.00000 MHz
1 sec	1000.000 kHz
10 sec	000.0000 kHz
MANUAL START = continuous count at 1 $\mu$ s rate	
MANUAL STOP = continuous display of last count	

Figure 3-4. Frequency Measurements




1. Turn SAMPLE RATE control clockwise from POWER OFF position to turn counter on.
2. Set function switch to desired FREQUENCY GATE TIME.
3. Set SENSITIVITY switch to CHECK to verify proper counter operation.
4. Connect unknown signal to the INPUT jack.
5. Change SENSITIVITY switch to 10; if there is no count or if count is uncertain, progressively set SENSITIVITY switch to lower ranges. Adjust -LEVEL+ control, if necessary, for proper triggering.
6. Read frequency from display. Decimal point is correctly positioned and correct measurement unit (kHz or MHz) is displayed.

Figure 3-5. Period Measurements




1. Turn counter on with SAMPLE RATE control.
2. Set function switch to desired PERIODS AVERAGED.
3. Set SENSITIVITY switch to CHECK to verify proper counter operation.
4. Connect unknown signal to the INPUT jack.
5. Turn SENSITIVITY switch clockwise to first position which gives steady count. Adjust -LEVEL+ control for proper triggering.
6. Read period from display; decimal point is correctly positioned and measurement unit ( $\mu$ s or ms) is displayed.

Figure 3-6, Totalizing Operation



1. Turn counter on with SAMPLE RATE control.
2. Set function switch to MANUAL START.
3. Set SENSITIVITY switch to CHECK to verify proper counter operation. Counter should count continuously at 1  $\mu$ s rate.
4. Connect unknown signal to INPUT jack.
5. Change SENSITIVITY switch to 10; if there is no count or if uncertain, switch to lower ranges. Adjust -LEVEL+ control for proper triggering.
6. Set function switch to MANUAL STOP.
7. Reset count to zero.
8. At desired time to begin count, set function switch to MANUAL START.
9. At desired time to end count, set function switch to MANUAL STOP.
10. Read accumulated count from display.

Figure 3-7. Ratio Measurements



Proceed as follows to measure the ratio between two frequencies ( $f_1/f_2$ ):


Higher frequency  $f_1$  may be between 1 kHz and 10 MHz.

Lower frequency  $f_2$  must be less than 1 MHz for single period and less than 2 MHz for multiple period measurements.

1. Turn counter on with SAMPLE RATE control.
2. Set function switch to desired PERIODS AVERAGED.
3. Connect higher frequency  $f_1$  to FREQ STD connector on rear panel and set FREQ STD switch to EXT.

4. Set SENSITIVITY switch to 10V rms position.
5. Connect lower frequency  $f_2$  to INPUT connector.
6. Turn SENSITIVITY switch clockwise until stable count is displayed. Adjust -LEVEL control for proper triggering.
7. Set function selector to PERIODS AVERAGED multiplier which gives the desired resolution.
8. Divide display by period multiplier to obtain  $f_1/f_2$ . Disregard decimal point and measurement units.

Figure 3-8. Time Interval Measurements



1. Turn counter on with SAMPLE RATE control.
2. Set function switch to 1 PERIODS AVERAGED.
3. Set FREQ-PER/TIME INT switch to TIME INT.
4. Connect start and stop control signals to START and STOP jacks.
5. Trigger stop signal.
6. Reset counter.
7. Trigger start signal.
8. Trigger stop signal.
9. Read time interval from display.

## NOTE

In the 1 PERIODS AVERAGED function, decimal point and measurement unit is correct.

# THEORY

## SECTION IV

### THEORY OF OPERATION

#### 4-1. INTRODUCTION

4-2. The Electronic Counter measures frequencies between 3 Hz and 12.5 MHz with seven digit display. In addition, time interval, period, and ratio measurements can be made. An internal 1 MHz time base frequency is standard and provides the clock signal for counting. Four line BCD code is supplied with assigned weights of 1, 2, 4, 8 and "1" or high level positive with respect to the "0" or low level. This BCD code is available at the rear panel for use with a digital recorder. The self check operation mode permits counting the internal time base signal to insure that the decade counters, gates, function selector switch, input amplifier, and time base are operating.

#### 4-3. BLANKING

4-4. The blanking feature suppresses the display of insignificant zeros in the display. Blanking can be manually disabled with the rear panel storage switch off. This simultaneously disables the storage of input data. Thus, with no blanking or storage, the digital display will continuously change while the new count is being totalized.

#### 4-5. GATING AND LOGIC

4-6. The counter circuits make extensive use of integrated circuits. As a result, it is necessary to understand basic logic symbols and their application in gating. In the circuit diagrams, AND gate and OR gate symbols are used extensively. The following paragraphs and illustrations introduce logic symbols and their applications.

#### 4-7. Logic Symbols

4-8. The symbol shown in Figure 4-1A is for the basic AND function. The basic AND gate output is high if all inputs are high. The AND gate can have two or more inputs. The symbol in Figure 4-1D is for the basic OR gate. The basic OR gate output is high when one or more of its inputs is high. The OR gate can also have two or more inputs. A small circle at the input line of a logic symbol indicates a low (L) level activates the function. The symbol of Figure 4-1B shows a low input on all lines causes a high (H) output. A small circle at the output line of a logic symbol indicates a low (L) level when activated, as shown in Figure 4-1C. Thus, the small circle indicates inversion. This applies to both types of gates. Figure 4-2

Figure 4-1. Gate Symbols




Figure 4-2. Logic Function Comparison

A			B			C			D		
$X = \bar{A} \cdot \bar{B}$			$X = A \cdot B$			$X = \overline{A \cdot B}$			$X = \bar{A} \cdot \bar{B}$		
$X = A + B$			$X = \overline{A + B}$			$X = A + B$			$X = \bar{A} + \bar{B}$		
A	B	X	A	B	X	A	B	X	A	B	X
H	H	H	H	H	H	H	H	L	H	H	L
H	L	H	H	L	L	H	L	L	H	L	H
L	H	H	L	H	L	L	H	L	L	H	H
L	L	L	L	L	L	L	L	H	L	L	H



lists examples and truth tables for logic actions. When the output of the OR gate is inverted, it is referred to as a NOR gate. Similarly, an inverted AND gate output gives a NAND gate.

4-9. Two states exist in the binary system, high (H) and low (L). H is more positive than L. In positive logic the one state is more positive than the zero state. In negative logic the one state is less positive than the zero state. In positive or negative logic H always represents the more positive level. In this manual, positive logic is used.


#### 4-10. Multiple Input JK Flip-Flop

4-11. Figure 4-3 illustrates the specific JK flip-flop used for main flip-flop A4IC7. The distinguishing features of this JK flip-flop are the multiple input gates at the J and K inputs.

#### 4-12. JK Master-Slave Flip-Flop

4-13. The JK master-slave flip-flop is a bistable MV. A unique feature is that with a simultaneous high input to J and K, before the clock pulse, Q and  $\bar{Q}$  will change states after the clock pulse. Refer to Figure 4-4 and Table 4-1. The JK master-slave flip-flop triggers on the trailing edge of the clock pulse. The preset (P) and clear (C) inputs operate as follows: if a low is applied to the preset input,  $\bar{Q}$  will go low. If a low is applied to the clear input, Q will go low. In the JK master-slave flip-flop, either preset or clear can override all other inputs at any time.

Figure 4-3. Multiple Input JK Flip-Flop



4-2

Figure 4-4. JK Flip-Flop




Table 4-1. Truth Table

$t_n$		$t_n + 1$		$t_n = \text{before clock pulse}$ $t_n + 1 = \text{after clock pulse}$
J	K	Q	$\bar{Q}$	
0	0	$Q_n$	$\bar{Q}_n$	If J = 0 and K = 0, then Q and $\bar{Q}$ will not change from what they were before the clock pulse.
1	0	1	0	If J = 1 and K = 0, then Q will be a 1 and $\bar{Q}$ a 0 after clock pulse.
0	1	0	1	If J = 0 and K = 1, then Q will be a 0 and $\bar{Q}$ a 1 after a clock pulse.
1	1	$\bar{Q}_n$	$Q_n$	If J = 1 and K = 1 before clock, then after clock pulse Q and $\bar{Q}$ will change states.

#### 4-14. INPUT ATTENUATOR ASSEMBLY A1 Schematic Diagram Figure 8-7

4-15. Input Attenuator A1 includes SENSITIVITY switch S1 and associated mounted components in a shielded compartment. The -LEVEL- control A1R10 is mounted on the rear of the shield. In CHECK, 1 MHz from mainboard assembly A4 goes through S1 to input amplifier assembly A2. In 10, 1, and .1 positions, resistive dividers with capacitive compensation are switched in to attenuate the input signal. In .01, the input signal is applied straight through to A2.

#### 4-16. INPUT AMPLIFIER ASSEMBLY A2 Schematic Diagram Figure 8-8

4-17. Input Amplifier A2 provides about 33 dB gain, A2 output drives the shaping amplifier in next assembly A4. Source follower Q1, Q2 uses field effect transistor Q1 and feedback amplifier Q2 for isolation. Voltage gain of the stage is unity. Diodes CR1 and CR2 are limiters. Q3, Q4 and Q5, Q6 provide two stages of amplification to drive trigger Q7, Q8. This trigger drives pulse amplifier Q9, Q10. The pulse amplifier output then goes to next assembly A4. Q11, with A1R1, adjusts bias level for the trigger circuit.

02430-3

**4-18. 1 MHz OSCILLATOR ASSEMBLY A3**  
Schematic Diagram Figure 8-9

4-19. A3 1 MHz oscillator contains oscillator Q1, buffer amplifier Q2, and associated components.

**4-20. MAIN BOARD ASSEMBLY A4**  
Schematic Diagram Figure 8-10

4-21. Main board assembly A4 is shown on three pages in the schematic of this manual. Flow diagrams at the back of this manual show the signal path through the main board circuits for operation in the frequency, period, ratio, and time interval modes. On these flow diagrams the input signal is a heavy line while the time base signal is a dashed line.

**4-22. A4 MAIN BOARD**

4-23. INPUT CIRCUIT. The Counter INPUT signal, after processing by the input attenuator (A1) and amplifier (A2), is connected to the main board (A4) through A4J2(3) to shaping amplifier Q4. The Q4 collector output is connected to two inputs, pins 1 and 4 of IC5, the function control selector.

4-24. BUFFER AND SCHMITT TRIGGER. The internal time base signal at A4J2(11) is amplified and isolated by A4Q1 and the output of Q1 is applied to IC6C(1). From Q1 the 1 MHz signal is also supplied to J4 for external use and to A1 for use as a CHECK signal. In the EXT FREQ STD mode the external time base signal is applied through J4 and A4J2(H) to a Schmitt trigger composed of A4Q2, Q3, and Q5. The Schmitt trigger output is applied to IC6C(2).

4-25. SIGNAL-TO-BE COUNTED SELECTOR. The gate formed by IC5A-B-C controls which signal is counted. When IC5A(5) is enabled by a high (FREQUENCY mode) the pulses at IC5A(4) (which are derived from the counter input signal through A2 and A4Q4) are steered through IC5A and B to the main gate for counting. When IC5C(3) is enabled by a high (PERIOD mode) the time base signal at IC5C(2) (from A3 through A4Q1, Q2, Q3, Q5, and IC6C) is steered through IC5C and IC5B to the main gate to be counted.

4-26. MAIN GATE CONTROL SELECTOR. The gate formed by IC5D-E-F selects the signal which will control the Main Gate. When IC5D(13) is enabled by a high (PERIOD mode), the pulses at IC5D(1), which are derived from the counter input signal, are steered through IC5D and E to decade divider IC3A. In "1 PERIOD" mode the output of IC5E(8) are directly through IC5D and B to the main gate control flip-flop, IC7(12), as the CLOCK signal. When IC5F(9) is enabled by a high (FREQUENCY mode) the 10 kHz (or external frequency standard divided by 10) from IC4A(13) is steered through IC5F and E to decade divider IC3A(2) input.

4-27. DECADE DIVIDERS (IC3, IC2, and IC1). The output of main gate control selector, IC5E(8) is applied

to the input, IC3A(2), of the decade divider string (IC3A, IC3B, IC2A, IC2B, and IC1A). Each IC section of the decade divider string divides its pin 2 or 10 input signal by 10, and supplies the 10 output at pin 4 or 12 to the next divider. A gated output is at pin 13 or 5. The gate control (enabled by a ground) is applied to pin 14 or 6. The function-range switch S2 selects which decade divider gated output is enabled and applied through IC6B to the main gate flip-flop, IC7(12).

4-28. SAMPLE RATE Flip-Flop (IC9A). This is a master-slave flip-flop. With the J input connected to +5.1 V (high) and the K input connected to ground (low) if a negative edge is applied to the CLK (clock) input, the flip-flop will set ( $Q=1$ ). A low applied to the CLR (clear) will make  $Q=0$  regardless of the J and K input levels.

4-29. RESET Flip-Flop (IC9B). The reset flip-flop is the same type as the sample rate flip-flop.

4-30. COUNTER MAIN GATE LOGIC. When the main gate flip-flop (IC7) is cleared (reset) IC7 $\bar{Q}$  is high and Q is low. The high from IC7 $\bar{Q}$  closes the main gate (Q14-Q13), Q14 is on. The low from IC7Q output is connected to IC7J and the low is inverted to high. Both IC7J1 and J2 are high because IC9A and IC9B are cleared, making both  $\bar{Q}$  outputs high. With IC7J high and IC7K low (the Q output low is connected to K1 input which makes the K low), a positive transition at the CLK input will set the main gate flip-flop. Then IC7Q will be high and  $\bar{Q}$  will be low. With  $\bar{Q}$  low Q14 is switched off (the main gate is open).

4-31. A pulse signal to Q13 base can switch Q13 off producing a positive pulse at the Q14-Q13 collectors. This is the pulse to be counted. When the main gate flip-flop is set, as described in the preceding paragraph, IC7Q is high and  $\bar{Q}$  is low. The IC7 output is connected to IC7J and K1. This makes IC7J low and K input high, which allows the main gate flip-flop to be reset by the next CLK pulse, closing the main gate.

4-32. The main gate flip-flop Q output is connected to the CLK input of the sample rate flip-flop, IC9A. The sample rate flip-flop will set when the CLK input goes from high to low. When set, the sample rate flip-flop Q output goes high and  $\bar{Q}$  goes low. The sample rate flip-flop  $\bar{Q}$  output is connected to the J1 input of the main gate. So with the sample rate flip-flop set there is a low at both J gate and K gate inputs of the main gate flip-flop. This disables the main gate flip-flop while the sample rate flip-flop is set.

4-33. The sample rate flip-flop Q output high goes through R29, R28, and the SAMPLE RATE control (R1) to C7 and the base of Q9. Capacitor C7 starts charging at a rate determined by R29, R28, and the setting of the SAMPLE RATE control. At some time during the charging of C7, Q9 and Q10 switch on which switches IC6A on and IC6A(6) goes low at the CLK input of IC9B, the reset flip-flop. This negative transition clocks the reset flip-flop and since J is tied high and K is tied low the flip-flop is set; Q goes high and  $\bar{Q}$  goes low. The reset flip-flop  $\bar{Q}$  output is connected to the J2 input of the main gate flip-flop. The reset flip-flop  $\bar{Q}$  output is also connected to the CLR (clear) input of

the sample rate flip-flop which is cleared by the low. The sample rate flip-flop Q output goes low forward biasing CR15 and allowing C7 to discharge through R29. When the reset flip-flop is set, the high at the Q output charges C8 through R30 and eventually switches Q8 on which applies a high to IC8C(5). The IC8(5) high is inverted at IC8C(6) and this low is applied to the reset flip-flop CLR input which clears the reset flip-flop. With the reset flip-flop cleared its  $\bar{Q}$  output goes high and this high is applied to the J2 input of the main gate flip-flop. The J1 input of the main gate flip-flop is high since the sample rate flip-flop is cleared with its  $\bar{Q}$  output high. With the main gate flip-flop J input high and K input low the main gate flip-flop is ready to be clocked by the next pulse from IC6B(8).

**4-34. ONE-SHOT AND DRIVER (A4Q12 and Q4Q11).** If less than a full pulse is received by Q12 from the main gate, Q14-Q13, the one-shot will either produce a standard width and amplitude pulse to Q11 or no pulse at all. This eliminates triggering on less than a full pulse.

**4-35.** The main gate signal from R42 goes to decade counter IC30 pin 9. BCD information from the first decade goes to buffer storage unit IC23 and also to next decade, IC29 pin 9. The buffer storage unit BCD information is taken off for a digital recorder from printed circuit connections on main board assembly jack A4J1. This is 1248 BCD code with "1" state positive. BCD information from the buffer storage unit goes to a decoder driver which has a 1248 "1" state negative input. The decoder unit then drives digital display tube DS7. The process is repeated in the other stages of counting, storage, and display.

**4-36. POSITIVE RESET SIGNAL.** When the reset flip-flop is set, the  $\bar{Q}$  output is low and IC8E inverts the low for the positive reset signal.

The positive reset signal resets the decade dividers IC1, IC2, IC3, and the decade counters IC24 to IC30.

**4-37. PRINT COMMAND.** The print command from Q15 collector is high during display time.

**4-38. GATE LIGHT AMPLIFIER.** The gate light amplifier, Q16, is switched by the main gate flip-flop  $\bar{Q}$  output. The gate light is on when Q16 is off. The R45 and C12 circuit stretches short pulses to insure flashing the gate light for short gate times.

**4-39. TIME INTERVAL START-STOP.** In the START mode the main gate is held open continuously by the low applied to the PRE (preset) input of IC7. While the main gate is open the counter input signal is being counted as pulses and displayed. When the function switch is moved to STOP the main gate is closed and the total of the signals counted while the gate was open is displayed. Both START and STOP functions can be remotely controlled through back panel connectors.

**4-40. BUFFER STORAGE TRANSFER SIGNAL.** At the end of the gate time the IC9AQ output goes from high to low and this signal is coupled through R23 and C6 to the base of Q7 which is momentarily switched

off and the Q7 collector (and IC8D(9)) goes high. The output of IC8D goes low, which is the transfer signal to the buffer storage units. If the STORAGE switch is OFF the output of IC8D is continuously low which is the buffer storage units.

**4-41. DECADE DIVIDERS.** Decade dividers IC1 through IC4 are 1248 code dividers which divide by 10. The input is at pin 2 or 10 and the output is at pin 4 or 12. IC3, 2, and 1 have gated outputs from pin 5 or 13. IC4 has pin 14 or 6 permanently forced low; thus, the output is from pin 5 at all times.

**4-42. DECADE COUNTERS.** Decade counter IC30 is a high-speed, blanking decade. Input is on pin 9 and the output is from pin 8. It provides a negative 1248 BCD code to buffer storage unit IC23. Decade counters IC24, IC25, IC26, IC27, IC28, and IC29 are low frequency blanking type decades. Blanking occurs when the storage switch is on and a low is applied to pin 10 of IC24, IC25, IC26, and IC27. IC26 and IC27 blanking may be over-ridden by a high to pin 10 controlled by function switch S2E. The 1248 BCD code drives the buffer storage units.

**4-43. BUFFER STORAGE UNITS.** These units have 4 inputs and 8 outputs. Four outputs are in phase with the input while the other 4 are not. When a low transfer pulse is applied to pin 5, the outputs assume the state of the input. When the low is removed, the outputs remain in their last state until a neutral transfer pulse is applied.

**4-44. DECODER DRIVER UNITS.** Decoder drivers are BCD-to-decimal decoders with 4 inputs and 10 outputs. A low from the decoder driver to a number in the digital display tube will light that number.

#### **4-45. DECIMAL POINT AND MEASUREMENT UNITS ASSEMBLY A5** Schematic Diagram Figure 8-9

**4-46.** Neon lamps DS1 through DS3 are decimal point lights. Neon lamps DS4 through DS7 are the measurement unit lights. All are controlled by function switch S2 on the front panel.

#### **4-47. POWER SUPPLY ASSEMBLY A6** Schematic Diagram Figure 8-11

**4-48. GENERAL.** Four regulated voltage sources of +175, +5, -5.8, and +5.1 volts are on power supply assembly A6. These are the operating voltages for the instrument. In the following discussion, complete reference designations are used to identify components. This is to prevent confusion between identifying components on the chassis and components on power supply assembly A6.

**4-49. PRIMARY POWER.** Either 115 Vac or 230 Vac is connected through fuse F1 and power switch S1. Slide switch S4 on the rear panel connects T1 primary

windings in parallel for 115 Vac operation or in series for 230 Vac operation.

4-50. +175 VOLT SUPPLY. The +175 volt supply includes full wave rectifier diodes A6CR1 through A6CR4. Series regulator A6Q1 is controlled by variations of the output voltage compared to the zener-controlled A6Q1 base voltage. A6Q4 limits the output current.

4-51. +5/-5.8 VOLT SUPPLY. This supply consists of a full wave rectifier filtered by A6C3. A regulated 12

volt's is set by A6CR16, A6CR15, and A6Q2; a center ground is set by A6Q7 and A6R9. A6Q3 regulates the total voltage by controlling the current.

4-52. +5.1 VOLT SUPPLY. This supply consists of full wave rectifier diodes A6CR0 through A6CR12 with filtering by A6C2, A6C5. Series regulator Q1 is driven by A6Q5. Voltage level is controlled by reference amplifier A6Q6 with bias set by A6R10. Thermistor A6RT1 compensates for changes in current. Further filtering is by A6C6 and A6C7.

# MAINTENANCE

## SECTION V

### MAINTENANCE

#### 5-1. INTRODUCTION

5-2. This section provides maintenance and service information for the Model 5216A. Included are: table of recommended test equipment; in-cabinet performance check; troubleshooting procedures; plus repair and adjustment procedures.

#### 5-3. ASSEMBLY DESIGNATIONS

5-4. Table 5-1 lists the designation, name, and part number of assemblies used in the instrument.

#### 5-5. TEST EQUIPMENT

5-6. Recommended test equipment for troubleshooting and performance checking is listed in Table 5-2.

Table 5-1. Assembly Identification

Assy	Name	HP Part No.
A1	Input Attenuator	05216-6005
A2	Input Amplifier	05216-6003
A3	1 MHz Oscillator	05216-6010
A4	Main Board	05216-6013
A5	Decimal Point and Measurement Unit	05216-6004
A6	Power Supply	05216-6012
W1	Cable, Gate Light	05216-6014

Table 5-2. Recommended Test Equipment

INSTRUMENT	CHARACTERISTICS	RECOMMENDED TYPE
Low Frequency Oscillator	Range: 1 Hz to 100 kHz Output: 10 mV to 1 V rms	HP Model 202C
Signal Generator	Range: 50 kHz to 12.5 MHz Output: 10 mV to 3 V rms	HP Model 606B
Oscilloscope	Bandwidth: dc to 12.5 MHz Sensitivity: 10 mV to 10 V	HP Model 175A with 1755A and 1780A plug-ins
DC Voltmeter	Range: 0 to 155 V dc Accuracy: $\pm 1\%$ of full scale Input impedance: 100 megohms	HP Model 412A
Frequency Standard	Frequency: 1 MHz Level: 1 V rms	HP Model 107AK
Preset Counter	Output: positive or negative pulses (use inverter with positive pulses), variable time between pulses	HP Model 5214L
Power Supply	Range: +5 V, -15 V at 5 ma	HP Model 721A

#### 5-7. INSTRUMENT COVER REMOVAL

5-8. To remove top cover, take out two screws securing the rear of top cover to main chassis. Slide cover to rear about 1/4 inch, then lift rear of cover. To remove bottom cover, first set tilt bail at right angle with bottom cover. Then take out two screws securing the rear of cover to the main chassis. Remove rear plastic foot according to directions on foot. Slide cover to rear and remove. To install cover, reverse procedure.

#### WARNING

115/230V ac and dc supply wires are exposed when either cover is removed. Exercise extreme caution during troubleshooting, adjustment, or repair. Disconnect ac power from instrument before removing or replacing covers or assemblies.

#### 5-9. IN-CABINET PERFORMANCE CHECK

5-10. The in-cabinet performance check outlined in Table 5-3 lists checks to verify specifications. The Performance Check Test Record page can be filled out during the checks to provide a permanent record of performance of each instrument. The in-cabinet performance checks can be used:

a. As part of an incoming inspection check of instrument specifications;

b. Periodically, for instrument used in systems where maximum reliability is of utmost importance;

c. As part of a troubleshooting procedure to locate troublesome circuits, and

d. After any repairs or adjustments, before returning instrument to regular service.

## 5-11. TROUBLESHOOTING

### 5-12. General

5-13. Trouble isolation can best be accomplished by first obtaining all possible information from the controls, indicators, and connectors; then logically applying this information to locate the defective circuit or component. Operating procedures in Section III and circuit diagrams in Section VIII can be used to help understand operation. Table 5-1 lists the printed circuit assemblies in the instrument. Figure 5-2 shows the location of assemblies and chassis-mounted components in the instrument. Refer to component location figures, voltages, and waveforms with the schematic diagrams in Section VIII. The performance check (Table 5-3) and troubleshooting tables 5-4 and 5-5 are also useful for locating trouble.

### 5-14. Removal of Main Board Assembly A4

5-15. To remove main board assembly A4:

a. Remove the top and both side covers (see Paragraph 5-7).

b. Remove front panel window by sliding it out either side.

c. Reach inside the side castings and gently lift sides of main board. Pull the board forward with the fingers.

d. After board is started, remove connector XA4.

e. Push or pull board out of counter being careful to keep board moving in a straight line.

f. To replace board, reverse the above procedure.

Make sure connector XA4 is reconnected and none of the wires are pinched by the board.

Table 5-3. In-Cabinet Performance Check

## FREQUENCY MEASUREMENTS

### 1. RANGE: 3 Hz to 12.5 MHz

a. Set Counter controls as follows:

SENSITIVITY . . . . .	.01 V
- LEVEL + . . . . .	adjust for stable count
Function Switch . . . . .	FREQUENCY, 1 sec
SAMPLE RATE . . . . .	ew out of POWER OFF

b. Connect Low Frequency Oscillator to Counter and Oscilloscope with BNC "T" connector (Oscilloscope is used to monitor input signal level).

c. Vary frequency from 3 Hz to 50 kHz, keeping signal level constant at 0.01 V rms (0.028 V peak-to-peak).

d. Substitute Signal Generator for Low Frequency Oscillator and set Counter function switch to .1 sec.

e. Vary frequency from 50 kHz to 12.5 MHz at 0.01 V rms (0.028 V peak-to-peak). Record results on test card.

### 2. SENSITIVITY: 0.01 V rms sine wave, 3 Hz to 12.5 MHz. Sensitivity checked by Procedure 1, Range Check.

### 3. GATE TIMES: 10, 1, .1, .01 seconds

a. Set Counter controls as follows:

SAMPLE RATE . . . . .	ew out of POWER OFF
SENSITIVITY . . . . .	.01 V
- LEVEL + . . . . .	adjust for stable count
Function Switch . . . . .	FREQUENCY .01 sec

b. Connect Signal Generator to INPUT jack. Set Signal Generator output to 10 MHz at 0.01 V rms.

c. Rotate function switch to each gate time and observe counter display for each setting. Record.

Table 5-3. In-Cabinet Performance Check Cont'd.

**FREQUENCY MEASUREMENTS Cont'd.**

4. READOUT: 7 significant digits with decimal point positioning and measurement unit display (kHz or MHz).

CHECK: counts 1 MHz for the GATE TIME selected by the function switch.

- a. Use Self Check procedure, Figure 3-3, Page 3-4.
- b. Record results on test card.

**TIME INTERVAL MEASUREMENTS**

RANGE: 10  $\mu$ s to 10 s

- a. Connect test setup shown in Figure 5-1 and set 5216A controls as follows:

SAMPLE RATE . . . . .	ew out of POWER OFF
SENSITIVITY . . . . .	not CHECK
- LEVEL + . . . . .	adjust for stable count
Function switch . . . . .	1 PERIOD AVERAGE
FREQ-PER TIME INT . . . .	TIME INT

- b. Set 5214L controls as follows:

SENSITIVITY . . . . .	CHECK
FUNCTION . . . . .	TIME
MULTIPLIER . . . . .	X1
SAMPLE RATE . . . . .	ew out of POWER OFF
"N" switches . . . . .	00100

- c. Reset both counters.
- d. "N" switches may be set at any number desired.
- e. Display should be the same on both counters. Record results on test card.

Figure 5-1. Test Setup for Time Interval Checks






Table 5-3. In-Cabinet Performance Check Cont'd.

PERIOD MEASUREMENTS

1. FREQUENCY RANGE SINGLE PERIOD: 3 Hz to 1 MHz
- a. Set Counter controls as follows:  
SENSITIVITY . . . . . .01 V  
- LEVEL + . . . . . adjust for stable count  
Function switch . . . . . 1 PERIOD AVERAGE  
SAMPLE RATE . . . . . cw out of POWER OFF
  - b. Connect Signal Generator to Counter.
  - c. Set Signal Generator output to 1 MHz at 0.01 V rms.
  - d. Counter should read .001 ms with decimal point correctly positioned and measurement unit displayed. Record results on test card.
2. FREQUENCY RANGE MULTIPLE PERIOD: 3 Hz to 2 MHz
- a. Set Counter controls as follows:  
SENSITIVITY . . . . . .01 V  
- LEVEL + . . . . . adjust for stable count  
Function switch . . . . . 10 PERIOD AVERAGE  
SAMPLE RATE . . . . . cw out of POWER OFF
  - b. Connect Signal Generator to Counter.
  - c. Set Signal Generator output to 2 MHz at 0.01 V rms.
  - d. Check Counter at each PERIOD AVERAGE setting, 10 through 100K. Record results on test card.
3. INPUT SENSITIVITY: 100 mV from 3 Hz to 1 kHz, 10 mV from 1 kHz to 2 MHz. Sensitivity checked in Range checks, procedures 1 and 2.

RATIO MEASUREMENTS

1. F1 FREQUENCY RANGE: 1 kHz to 10 MHz.
- a. Set Counter controls as follows:  
SENSITIVITY . . . . . .01 V  
- LEVEL + . . . . . adjust for stable count  
Function switch . . . . . 100 PERIOD AVERAGE  
SAMPLE RATE . . . . . cw out of POWER OFF  
FREQ STD . . . . . EXT  
STORAGE . . . . . ON
  - b. Connect f<sub>2</sub> 100 kHz frequency standard to INPUT jack.
  - c. Connect Signal Generator (f<sub>1</sub>) to FREQ STD jack on rear panel. Set output to 2 MHz at 1V rms.
  - d. Make checks indicated in the following table. Record results on test card.

f <sub>1</sub>	f <sub>2</sub>	X100 Periods Ratio Display
2.0 MHz	100 kHz	02000
1.5 MHz	100 kHz	01500
1.0 MHz	100 kHz	01000
500 kHz	100 kHz	00500
100 kHz	100 kHz	00100
50 kHz	100 kHz	00050
10 kHz	100 kHz	00010
1 kHz	100 kHz	00001

Table 5-3. In-Cabinet Performance Check Cont'd.

**RATIO MEASUREMENTS Cont'd.**

2. F2 FREQUENCY RANGE: 3 Hz to 1 MHz, Single Period  
3 Hz to 2 MHz, Multiple Period
- a. Set Counter controls as follows:
- |                           |                         |
|---------------------------|-------------------------|
| SENSITIVITY . . . . .     | .01 V                   |
| - LEVEL + . . . . .       | adjust for stable count |
| Function switch . . . . . | 10K PERIODS AVERAGED    |
| SAMPLE RATE . . . . .     | cw out of POWER OFF     |
| FREQ STD . . . . .        | EXT                     |
| STORAGE . . . . .         | ON                      |
- b. Connect  $f_1$  100 kHz frequency standard to FREQ STD jack on rear panel.
- c. Connect Signal Generator ( $f_2$ ) to INPUT jack. Set output to 2 MHz at .01 V rms.
- d. Make checks shown in the following table. Record results on test card.

$f_1$	$f_2$	Periods Averaged	$f_1/f_2$ Display
100 kHz	2 MHz	10K	00500
100 kHz	1.5 MHz	10K	00660
100 kHz	1 MHz	10K	01000
100 kHz	500 kHz	10K	02000
100 kHz	100 kHz	10K	10000
100 kHz	50 kHz	10K	20000
100 kHz	10 kHz	10K	100000
100 kHz	1 kHz	1K	100000
100 kHz	500 Hz	1K	200000
100 kHz	100 Hz	100	100000
100 kHz	50 Hz	100	200000
100 kHz	10 Hz	10	100000
100 kHz	3 Hz	1	33333

3. SENSITIVITY:  $f_1$ : 1 kHz to 2 MHz, 1 V rms minimum  
 $f_2$ : 3 Hz to 1 kHz, 100 mV rms; 1 kHz to 2 MHz, 10 mV rms  
Sensitivity checked in procedures 1 and 2, Range checks.

**TIME BASE**

## 1. TIME BASE FREQUENCY: 1 MHz

STABILITY: Aging Rate: +1 part in  $10^6$ /month  
 Temperature: +3 parts in  $10^5$  (+0° to +50°C)  
 +5 parts in  $10^6$  (+10° to +40°C)  
 Line Voltage: +1 part in  $10^6$  for +10% line voltage change

- a. Connect 1 MHz frequency standard to Oscilloscope trigger input.
- b. Connect Oscilloscope vertical input to Counter FREQ STD jack.
- c. Set Oscilloscope for external triggering and .1  $\mu$ s/cm sweep.
- d. Horizontal drift of Oscilloscope pattern in cm/sec is difference between standard frequency and Counter time base frequency in parts in  $10^6$ . Record.
- e. Record frequency difference. For long term stability, this test should be made daily for one month.
- f. Vary line voltage  $\pm 10\%$  and record frequency difference.
- g. Vary operating temperature from +10°C to +50°C and record frequency difference.

Table 5-3. In-Cabinet Performance Check Cont'd.

### TIME BASE Cont'd.

#### 2. OUTPUT FREQUENCY: 1 MHz at 3 V peak-to-peak

- a. Connect output of Counter FREQ STD jack to Oscilloscope vertical input.
- b. Oscilloscope should display a 1 MHz nonsinusoidal wave of 3 V peak-to-peak. Record frequency and amplitude on test card.

#### 3. EXTERNAL INPUT: 1 MHz sine wave, 1 V rms

- a. Connect 1 MHz standard frequency to Counter FREQ STD jack.
- b. Set INT/EXT switch to EXT.
- c. Perform self check procedure, Figure 3-3.
- d. Record results on test card.

### DISPLAY STORAGE

- a. Set Counter controls as follows:
 

SAMPLE RATE . . . . .	cw out of POWER OFF
SENSITIVITY . . . . .	CHECK
Function switch . . . . .	.01 sec
STORAGE . . . . .	OFF
- b. Counter should display 001.0000 MHz. The change in count should be visible in each digital display tube.
- c. Set STORAGE switch to STORAGE position. The counter should count, display, and hold 1.0000 MHz and provide a continuous display of the most recent count. Record results on test card.

### SAMPLE RATE

Variable from 50 ms to 5 sec.

- a. Set Counter controls as follows:
 

SAMPLE RATE . . . . .	POWER OFF
Function switch . . . . .	.01 sec
SENSITIVITY . . . . .	CHECK
- b. Turn counter SAMPLE RATE control slightly cw out of POWER OFF, and note that counter turns on.
- c. With SAMPLE RATE control in maximum position (ccw), observe gate light duration between gate closing and the following gate opening; it should be 50 ms.
- d. Increase SAMPLE RATE control clockwise to minimum sample rate. Observe gate light duration between gate closing and the following gate opening; it should be more than 5 seconds.
- e. Set SAMPLE RATE control to HOLD position. The last counter reading should remain displayed indefinitely. Record results on test card.

NOTE: This is a visual check and not an accurate check of the sample rate.

Table 5-3. In-Cabinet Performance Check Cont'd.

**GATE INDICATOR**

Front panel indication of main gate "open" state (GATE light on).

- a. Set Counter controls as follows:

SAMPLE RATE . . . . .	ew out of POWER OFF
SENSITIVITY . . . . .	CHECK
Function switch . . . . .	1 s

- b. Observe counter gate lamp, lamp should turn on and off at one second intervals. Record results on test card.

**RESET CAPABILITY**

A momentary control on the front panel that returns both the displayed and internal count to zero.

- a. Set Counter controls as follows:

SAMPLE RATE . . . . .	ew out of POWER OFF
SENSITIVITY . . . . .	CHECK
Function switch . . . . .	1 s

- b. Push front panel RESET pushbutton. Counter should reset and then start a new count.
- c. Rotate function switch. As function is changed the counter should reset and start another count.
- d. A remote contact closure or saturated NPN transistor to ground connected to RESET jack (rear panel) should reset counter and start a new count. Allow 30 ms between external reset pulse and start pulse.

**DIGITAL OUTPUT**

1. OUTPUT 4 LINE 1248 BCD CODE: Impedance 7500 ohm each line  
 "1" state level (H) +5 V  
 "0" state level (L) 0 V

- a. Impedance determined by BCD output circuit on main board assembly A4.

- b. Set Counter controls as follows:

SAMPLE RATE . . . . .	ew out of POWER OFF
Function switch . . . . .	.1 sec
SENSITIVITY . . . . .	.1 V

- c. Connect signal source to counter INPUT jack.

- d. Connect Oscilloscope to connections indicated on A4J1 to verify "0" state and "1" state levels. Oscilloscope will display step from "0" state (0 volts) to "1" state (+5 volts). Check all recorder outputs for "0" state and "1" state. Record on test card.

Table 5-3. In-Cabinet Performance Check Cont'd.

**DIGITAL OUTPUT Cont'd.**

**1. OUTPUT 4 LINE 1248 BCD CODE**

**A4J1 Pins**

17 } First Decoder A4IC33, Set  
16 } Low Frequency Oscillator  
15 } to 10 Hz at .1 V rms.  
18 }

6 } Second Decoder A4IC30, Set  
7 } Low Frequency Oscillator  
8 } to 100 Hz at .1 V rms.  
5 }

F } Third Decoder A4IC27, Set  
H } Low Frequency Oscillator  
J } to 1 kHz at .1 V rms.  
E }

R } Fourth Decoder A4IC24, Set  
N } Low Frequency Oscillator  
M } to 10 kHz at .1 V rms.  
P }

**A4J1 Pins**

L } Fifth Decoder A4IC21, Set  
9 } Signal Generator to 100 kHz  
10 } at .1 V rms.  
K }

11 } Sixth Decoder A4IC18, Set  
13 } Signal Generator to 1 MHz  
14 } at .1 V rms.  
12 }

S } Seventh Decoder A4IC15,  
V } Set Signal Generator to  
U } 10 MHz at .1 V rms.  
T }

**2. REFERENCE LEVELS: 0 volts and +5 volts, low impedance**

- a. Set SAMPLE RATE control slightly clockwise out of POWER OFF.
- b. Connect DC Voltmeter to DIGITAL RECORDER jack A4J1 pins 3, C to check +5 V positive reference and A4J1 pins 1, A for 0 V reference. Record results on test card.

**3. PRINT COMMAND: Positive step from 0 V to +5 V, dc coupled.**

- a. Connect Oscilloscope to DIGITAL RECORDER jack A4J1 pin 4.
- b. Set Counter controls as follows:  
SAMPLE RATE . . . . . cw out of POWER OFF  
SENSITIVITY . . . . . CHECK  
Function switch . . . . . .01 sec
- c. Oscilloscope should display the print command step (+5 V for each counting cycle). Record results on test card.

**4. HOLD-OFF REQUIREMENTS: -10 V to -15 V**

- a. Set Counter controls as follows:  
SAMPLE RATE . . . . . cw out of POWER OFF  
SENSITIVITY . . . . . CHECK  
Function switch . . . . . 10 sec  
STORAGE . . . . . OFF
- b. With DC Power Supply, apply inhibit voltage, -10 volts, to DIGITAL RECORDER jack A4J1 pin 2. The counter should stop until the inhibit voltage is removed. Record results on test card.
- c. Repeat step b using -15 volt inhibit voltage. Record on test card. This check can be made using any inhibit voltage from -10 to -15 volts.

## PERFORMANCE CHECK TEST CARD

Hewlett-Packard Model 5216A  
Electronic Counter  
Serial No. \_\_\_\_\_

Tests Performed by \_\_\_\_\_  
Date \_\_\_\_\_

DESCRIPTION	CHECK
<b>FREQUENCY MEASUREMENT</b>	
1. Range: 3 Hz to 12.5 MHz	<input type="checkbox"/> 3 Hz to 12.5 MHz
2. Sensitivity: .01 V rms sine wave, 3 Hz to 12.5 MHz	<input type="checkbox"/> .01 V
3. Gate Times: 10, 1, .1, .01 seconds	<input type="checkbox"/> 10 sec <input type="checkbox"/> 1 sec <input type="checkbox"/> .1 sec <input type="checkbox"/> .01 sec
4. Readout: 7 significant digits with decimal point and measurement unit display	<input type="checkbox"/> 7 digits
<b>TIME INTERVAL MEASUREMENT</b>	
1. Range: 10 $\mu$ s to 10 s	<input type="checkbox"/> 10 $\mu$ s to 10 s
<b>PERIOD MEASUREMENT</b>	
1. Range Single Period: 3 Hz to 1 MHz	<input type="checkbox"/> 3 Hz to 1 MHz
2. Range Multiple Period: 3 Hz to 2 MHz	<input type="checkbox"/> 3 Hz to 2 MHz
3. Sensitivity: .1 V, 3 Hz to 1 kHz; .01 V, 1 kHz to 2 MHz	<input type="checkbox"/> .1 V <input type="checkbox"/> .01 V
<b>RATIO MEASUREMENT</b>	
1. $f_1$ Frequency Range: 1 kHz to 2 MHz	Ratio $f_1/f_2$ <input type="checkbox"/> 02000 <input type="checkbox"/> 01500 <input type="checkbox"/> 01000 <input type="checkbox"/> 00500 <input type="checkbox"/> 00100 <input type="checkbox"/> 00050 <input type="checkbox"/> 00010 <input type="checkbox"/> 00001
2. $f_2$ Frequency Range: 3 Hz to 1 MHz Single Period 3 Hz to 2 MHz Multiple Period	<input type="checkbox"/> 00500 <input type="checkbox"/> 00660 <input type="checkbox"/> 01000 <input type="checkbox"/> 02000 <input type="checkbox"/> 10000 <input type="checkbox"/> 20000 <input type="checkbox"/> 10000 <input type="checkbox"/> 100000 <input type="checkbox"/> 200000 <input type="checkbox"/> 100000 <input type="checkbox"/> 200000 <input type="checkbox"/> 100000 <input type="checkbox"/> 33333

## PERFORMANCE CHECK TEST CARD

DESCRIPTION	CHECK
<b>RATIO MEASUREMENT Cont'd.</b>	
3. Sensitivity: $f_1$ 1 V rms min, 1 kHz to 2 MHz $f_2$ .1 V rms, 3 Hz to 1 kHz .01 V rms, 1 kHz to 2 MHz	<input type="checkbox"/> $f_1$ <input type="checkbox"/> $f_2$
<b>TIME BASE FREQUENCY: 1 MHz</b>	
1. Stability: Aging Rate: $\pm 1$ part in $10^6$ /month Temperature: $\pm 3$ parts in $10^5$ (0°C to +50°C) $\pm 5$ parts in $10^6$ (+10°C to +40°C) Line Voltage: $\pm 1$ part in $10^6$ for $\pm 10\%$ change	<input type="checkbox"/> less than $\pm 1$ part in $10^6$ /month <input type="checkbox"/> $\pm 3$ parts in $10^5$ <input type="checkbox"/> $\pm 5$ parts in $10^6$ <input type="checkbox"/> less than $\pm 1$ part in $10^6$
2. Output Frequency: 1 MHz, 3 V peak-to-peak	<input type="checkbox"/> 1 MHz, 3 V peak-to-peak
3. External Input: 1 MHz sine wave, 1 V rms	<input type="checkbox"/> 1 MHz
<b>SAMPLE RATE</b>	
Variable from 50 ms to 5 seconds	<input type="checkbox"/> less than 50 ms to greater than 5 seconds
<b>DISPLAY STORAGE</b>	
	<input type="checkbox"/> count stored
<b>GATE INDICATOR</b>	
Front panel indication of main gate "open" state.	<input type="checkbox"/> gate light flashes
<b>RESET CAPABILITY</b>	
Manual Reset switch Function switch Remote Reset	<input type="checkbox"/> counter resets <input type="checkbox"/> counter resets <input type="checkbox"/> counter resets
<b>DIGITAL OUTPUT</b>	
1. Output 4 line 1248 BCD Code: "1" state level +5V, "0" state level 0V	<input type="checkbox"/> +5 V <input type="checkbox"/> 0 V
2. Reference Levels: 0 volts and +5 volts low impedance	<input type="checkbox"/> +5 V A4J1 (3, C) <input type="checkbox"/> 0 V A4J1 (1, A)
3. Print Command: Positive step from 0 V to +5 V dc coupled.	<input type="checkbox"/> +5 volts A4J1 (4)
4. Hold-off Requirements: -10 V to -15 V	<input type="checkbox"/> -10 V A4J1 (2) <input type="checkbox"/> -15 V A4J1 (2)

Figure 5-2. Bottom and Sides Internal Views






Table 5-4. Front Panel Troubleshooting Check





Table 5-4. Front Panel Troubleshooting Check Cont'd.



## 5-16. Substitution

5-17. Replacing the assembly suspected of trouble with a spare assembly known to be operating can greatly simplify troubleshooting. When a defective assembly is found, the trouble can then be traced to individual components. The defective assembly can be shipped to the nearest Hewlett-Packard Sales and Service office for repair.

## 5-18. Printed Circuit Component Replacement

5-19. Component lead holes in the circuit boards have plated walls to ensure good electrical contact between conductors on opposite sides of the board. To prevent damage to this plating, apply heat sparingly and work carefully. The following replacement procedure is recommended:

a. Remove defective component by first heating terminals on either side of board until solder melts. Then gently remove part with long nose pliers. Use a clean, 37 watt soldering iron.

b. Melt solder in component lead holes. Clean holes with toothpick or wooden splinter. Do not use a metal tool for cleaning holes.

c. Shape component leads and insert into cleaned holes. Solder into place using heat and solder sparingly; a heat sink such as long nose pliers or a commercial heat sink should be used when replacing transistors or diodes.

d. Through-hole plating breaks are indicated by separation of the round conductor pad from other side of the board. To repair breaks, press conductor pad against board and solder replacement component lead to conductor pads on both sides of board.

## 5-20. ADJUSTMENTS

5-21. Adjustment procedures for the 10 MHz Oscillator and the Power Supply are given in Paragraphs 5-22 and 5-24. The listings are in the preferred order of adjustment.

### 5-22. Power Supply Assembly A6

5-23. To adjust the +5.1V supply:

- Connect DC Voltmeter to A6(2).
- Turn on Counter.
- Adjust A6R7 for +5.1V  $\pm$  .02V.

### 5-24. 1 MHz Oscillator Assembly A3

5-25. To check Oscillator frequency, use test setup in Figure 5-3.

#### NOTE

For best long term stability, the Counter should warm up for 24 hours before checking frequency.

- Connect 1 MHz standard to EXT SYNC input on Oscilloscope.
- Connect output from 5216A FREQ STD jack to Oscilloscope Vertical Input.
- Adjust A3C5 (Coarse) and A3C6 (Fine) until sine wave display is stationary.

Figure 5-3. Oscillator Frequency Test Setup




Table 5-5. Function Switch Connections to Main Board A4

FUNCTION	WAFER S2A to A4 Pin	WAFER S2B to A4 Pin	WAFER S2C to A5	WAFER S2DR to A5	WAFER S2E to A4 Pin
PERIOD: 1	0	0	#3	MS	NONE
10	E	0	#2	MS	14
100	D	0	#1	MS	13, 14
1K	C	0	#3	$\mu$ S	NC
10K	B	0	#2	$\mu$ S	14
100K	A	0	#1	$\mu$ S	13, 14
FREQ: .01	D	0	#3	MHz	14
.1	C	0	#2	MHz	13, 14
1	B	0	#1	kHz	NC
10	A	0	#2	kHz	14
MANUAL START	L	0	NONE	A4(J)	13, 14
MANUAL STOP	M + STOP BNC	0	NONE	NC	13, 14
GROUNDED TO ACTIVATE FUNCTION AS SHOWN					+5V -JN

# PARTS LIST

SECTION VI  
REPLACEABLE PARTS

## 6-1. INTRODUCTION

6-2. This section contains information for ordering replacement parts. Table 6-1 lists parts in alpha-numerical order of their reference designators and indicates the description and HP part number of each part, together with any applicable notes. Table 6-2 lists parts in alpha-numerical order of their HP part number and provides the following information on each part.

- Description of the part (see list of abbreviations below).
- Typical manufacturer of the part in a five-digit code; see list of manufacturers in Table 6-3.
- Manufacturer's part number.
- Total quantity used in the instrument (TQ column).

6-3. Miscellaneous parts are listed at the end of Table 6-1.

## 6-4. ORDERING INFORMATION

6-5. To obtain replacement parts, address order or inquiry to your local Hewlett-Packard Sales and Service office (see lists at rear of this manual for addresses). Identify parts by their Hewlett-Packard part numbers.

6-6. To obtain a part that is not listed, include:

- Instrument model number.
- Instrument serial number.
- Description of the part.
- Function and location of the part.

REFERENCE DESIGNATORS			
A	assembly	F	fuse
B	motor	FL	filter
BT	battery	IC	integrated circuit
C	capacitor	J	jack
CP	coupler	K	relay
CR	diode	L	inductor
DL	delay line	LS	loud speaker
DS	device signaling (lamp)	M	meter
E	misc electronic part	MK	microphone
MP	mechanical part	Q	plug
P	transistor	R	resistor
RT	thermistor	S	switch
T	transformer	TP	test point
TB	terminal board	U	integrated circuit
		V	vacuum tube, neon tube, photocell, etc.
		VR	voltage regulator
		W	wire
		X	socket
		Y	crystal
		Z	tuned cavity, network

ABBREVIATIONS			
AC	amperes	H	henries
AF	automatic frequency control	HDW	hardware
AMPL	amplifier	HPX	hexagonal
BFO	beat frequency oscillator	HG	mercury
BF CU	beryllium copper	HR	hour(s)
BR	brider head	HZ	hertz
BP	bandpass	IF	intermediate freq
BRS	base	IMPG	integrated
BWO	backward wave oscillator	INCD	incandescent
CCW	counter-clockwise	INCL	include(s)
CER	ceramic	INS	insulation(ed)
CMO	cabinet mount only	INT	internal
COEF	coefficient	K	kilo - 1000
COM	common	LH	left hand
COMP	composition	LTN	linear taper
COMPL	complex	LK WASH	lock washer
CONN	connector	LOG	logarithmic taper
CP	cadmium plate	LPF	low pass filter
CRT	cathode-ray tube	M	mil(s) - 10 <sup>-3</sup>
CR	clockwise	MEG	meg - 10 <sup>6</sup>
DEPC	deposited carbon	MET FILM	metal film
DR	drive	MET OX	metallic oxide
ELECT	electrolytic	MFR	manufacturer
ENCAP	encapsulated	MHZ	mega hertz
EXT	external	MINAT	miniature
F	farads	MOM	momentary
FB	flat head	MOS	metal oxide substrate
FLH	flashing head	MTG	mounting
FSD	fixed	MY	"mylar"
G	giga (10 <sup>9</sup> )	N	nano (10 <sup>-9</sup> )
GE	germanium	N/C	normally closed
GL	glass	NE	neon
GND	ground(ed)	NPL	nickel plate
N/O	normally open	NOM	nominal
NPO	negative positive zero (zero temperature coefficient)	NPN	negative-positive-negative
NRRF	not recommended for field replacement	NSR	not separately replaceable
ORD	order by description	OH	oval head
OX	oxide	P	peak
P	peak	PC	printed circuit
PF	picofarads - 10 <sup>-12</sup> farads	PH BRZ	phosphor bronze
PH BRZ	phosphor bronze	PHL	Phillips
PIV	peak inverse voltage	PNP	positive-negative-positive
POT	potentiometer	P/O	part of
PP	peak-to-peak	POLY	polystyrene
PT	point	PORC	porcelain
PWV	peak working voltage	POS	position(s)
RECT	rectifier	POT	potentiometer
RF	radio frequency	PP	peak-to-peak
RH	round head or right hand	PT	point
		PWV	peak working voltage
		RECT	rectifier
		RF	radio frequency
		RH	round head or right hand
		U	integrated circuit
		V	vacuum tube, neon tube, photocell, etc.
		VR	voltage regulator
		W	wire
		X	socket
		Y	crystal
		Z	tuned cavity, network

AMP	ampere	HM	henry	N/O	normally open	HMO	rack mount only
AF	automatic frequency control	HDW	hardware	NOM	nominal	RMS	root-mean square
AMPL	amplifier	HPX	hexagonal	NPO	negative positive zero (zero temperature coefficient)	RWV	reverse working voltage
BFO	beat frequency oscillator	HG	mercury	NPN	negative-positive-negative	S-B	slow blow
BF CU	beryllium copper	HR	hour(s)	NRRF	not recommended for field replacement	SCR	silicon controlled rectifier
BR	brider head	HZ	hertz	NSR	not separately replaceable	SE	selenium
BP	bandpass	IF	intermediate freq	ORD	order by description	SI CT	section(s)
BRS	base	IMPG	integrated	OH	oval head	SEMICON	semiconductor
BWO	backward wave oscillator	INCD	incandescent	OX	oxide	SI	silicon
CCW	counter-clockwise	INCL	include(s)	P	peak	SHL	silver
CER	ceramic	INS	insulation(ed)	PC	printed circuit	SL	slide
CMO	cabinet mount only	INT	internal	PF	picofarads - 10 <sup>-12</sup> farads	SPG	spring
COEF	coefficient	K	kilo - 1000	PH BRZ	phosphor bronze	SPL	special
COM	common	LH	left hand	PHL	Phillips	SST	stainless steel
COMP	composition	LTN	linear taper	PIV	peak inverse voltage	SH	split ring
COMPL	complex	LK WASH	lock washer	PNP	positive-negative-positive	STL	steel
CONN	connector	LOG	logarithmic taper	P/O	part of	TA	tantalum
CP	cadmium plate	LPF	low pass filter	POLY	polystyrene	TD	time delay
CRT	cathode-ray tube	M	mil(s) - 10 <sup>-3</sup>	PORC	porcelain	TGL	toggle
CR	clockwise	MEG	meg - 10 <sup>6</sup>	POS	position(s)	THD	thread
DEPC	deposited carbon	MET FILM	metal film	POT	potentiometer	TI	titanium
DR	drive	MET OX	metallic oxide	PP	peak-to-peak	TOL	tolerance
ELECT	electrolytic	MFR	manufacturer	PT	point	TRM	trimmer
ENCAP	encapsulated	MHZ	mega hertz	PWV	peak working voltage	TWT	traveling wave tube
EXT	external	MINAT	miniature	RECT	rectifier	U	micro - 10 <sup>-6</sup>
F	farads	MOM	momentary	RF	radio frequency	VAR	variable
FB	flat head	MOS	metal oxide substrate	RH	round head or right hand	VDCW	dc working volts
FLH	flashing head	MTG	mounting			W	with
FSD	fixed	MY	"mylar"			W	with
G	giga (10 <sup>9</sup> )	N	nano (10 <sup>-9</sup> )			WIV	working inverse voltage
GE	germanium	N/C	normally closed			WW	wirewound
GL	glass	NE	neon			W/O	without
GND	ground(ed)	NPL	nickel plate				

01194-14

**Table 6-1. Reference Designation Index**

Reference Designation	Q Part No.	Description #	Note
A1	05716-0005	ABSTRACTIFICATION SWITCH	
	05716-0001	CABLE TATTEN SWITCH	
	0500-0710	CUMPLER SWITCH SHAF	
	0770-0100	KNOWLEDGE FILM 0.125 DIA SHAF	
	0770-0005	KNOWLEDGE FILM 0.125 DIA	
	05716-0005	COVER ATTEN SWITCH	
	0100-0010	INDUCTION INDUCTION	
	0100-0010	INDUCTION INDUCTION	
	0100-0010	INDUCTION INDUCTION	
A1C1	0100-2200	LIFER CER 10 PF 50 500VDC	
A1L1	0100-2201	LIFER CER 2.2x0.25 PF 500VDC	
A1L1	0100-2200	LIFER CER 20 PF 50 500VDC	
A1L4	0100-0710	LIFER MICA 2000 PF 1	
A1L5	0100-2200	LIFER CER 10 PF 50 500VDC	
A1L6	0100-2200	LIFER CER 1.0x0.25 PF 500VDC	
A1L7	0100-0010	LIFER CER 0100 1000 PF 50-200 1000VDC	
A1C1	1901-0370	INDUCTION INDUCTION	
A1C1	1901-0370	INDUCTION INDUCTION	
A1P1	1251-0070	PLUG IN MICA PALE	
A1A1	0757-0150	NIFER MET FILM 100K OHM 10 1/4W	
A1A2	0757-0770	NIFER MET FILM 100K OHM 10 1/4W	
A1A3	0757-0150	NIFER MET FILM 1.00 OHM 10 1/4W	
A1A4	0757-0150	NIFER MET FILM 10.0K OHM 10 1/4W	
A1A5	0757-0150	NIFER MET FILM 100K OHM 10 1/4W	
A1A6	0683-1015	NIFER LUMP 100 OHM 5% 1/4W	
A1A7	0757-0770	NIFER MET FILM 100K OHM 10 1/4W	
A1A8	0683-1015	NIFER LUMP 750 OHM 5% 1/4W	
A1A9	0683-1015	NIFER LUMP 100K OHM 5% 1/4W	
A1A10	0683-1015	NIFER LUMP 2K OHM 5% 1/4W	
A1A11	0683-1015	NIFER LUMP 100 OHM 5% 1/4W	
A1A12	0100-2407	INDUCTION INDUCTION	
A2	05716-0005	ABSTRACTIFICATION SWITCH	
	05716-0001	CABLE TATTEN SWITCH	
A2L1	0100-0710	LIFER CER 1.0 PF 100 500VDC	
A2L2	0100-2200	LIFER CER 0.2 0.25 PF 500VDC	
A2L3	0100-0710	LIFER CER 1.0 PF 100 500VDC	
A2L4	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L5	0100-0710	LIFER CER 100 PF 200 500VDC	
A2L6	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L7	0100-0710	LIFER CER 100 PF 200 500VDC	
A2L8	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L9	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L10	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L11	0100-0710	LIFER CER 10 PF 100 500VDC	
A2L12	0100-0710	LIFER CER 10 PF 100 500VDC	

\* See introduction to this section for ordering information

Reference Designation	Q Part No.	Description #	Note
A7L1	0150-0001	REFID CEM Q.O. OF 400-208 100VAC	
A7A1	1501-0000	UNDETERMINED JONA JONY	
A701	1555-0001	WEL PET M-CHAN	
A707	1551-0016	WEL PNP 2N3006	
A703	1555-0015	WEL NPN 2N3004	
A706	1555-0015	WEL PNP SELECTED FROM 2N1251	
A705	1555-0015	WEL NPN	
A706	1551-0016	WEL PNP SELECTED FROM 2N1251	
A707	1555-0016	WEL NPN SELECTED FROM 2N1251	
A708	1555-0019	WEL NPN SELECTED FROM 2N1251	
A709	1555-0015	WEL NPN 2N3004	
A710	1551-0016	WEL PNP 2N3006	
A711	1551-0016	WEL PNP 2N3006	
A701	0001-0015	REFID LUMP 470 OHM 5% 1/4W	
A702	0000-1051	REFID LUMP 1M OHM 1% 1/4W	
A703	0757-0027	REFID FLN 1.5K OHM 2% 1/4W	
A704	1000-0025	REFID LUMP 2000 OHM 5% 1/4W	
A705	0000-0135	REFID LUMP 12K OHM 5% 1/4W	
A706	0001-0025	REFID LUMP 2700 OHM 5% 1/4W	
A707	0000-1025	REFID LUMP 1000 OHM 5% 1/4W	
A708	0757-0025	REFID FLN 100 OHM 2% 1/4W	
A709	0757-0027	REFID FLN 1300 OHM 2% 1/4W	
A710	0757-0027	REFID FLN 5.6K OHM 2% 1/4W	
A711	0000-1025	REFID LUMP 1000 OHM 5% 1/4W	
A712	0001-0025	REFID LUMP 2700 OHM 5% 1/4W	
A713	0000-1025	REFID LUMP 12K OHM 5% 1/4W	
A714	0000-1025	REFID LUMP 1000 OHM 5% 1/4W	
A715	0757-0025	REFID FLN 100 OHM 2% 1/4W	
A716	0757-0027	REFID FLN 5.6K OHM 2% 1/4W	
A717	0757-0025	REFID FLN 1.5K OHM 2% 1/4W	
A718	0000-1025	REFID LUMP 1000 OHM 5% 1/4W	
A719	0757-0016	REFID FLN 390 OHM 2% 1/4W	
A720	0001-1035	REFID LUMP 10K OHM 5% 1/4W	
A721	0757-0016	REFID FLN 390 OHM 2% 1/4W	
A722	0757-0026	REFID FLN 1.5K OHM 2% 1/4W	
A723	0757-0016	REFID FLN 390 OHM 2% 1/4W	
A724	0000-0001	REFID LUMP 680 OHM 5% 1/4W	
A725	0757-0015	REFID FLN 430 OHM 2% 1/4W	
A726	0757-0025	REFID FLN 12K OHM 2% 1/4W	
A727	0006-3166	REFID FLN 6.8K OHM 2% 1/4W	
A728	0757-0010	OSCILLATION ASSY	

\* See introduction to this section for ordering information.

Reference Designation	Part No.	Description #	Note
	05216-2010	BOARD BLANK PL	
ABC1	0180-0291	CIRCUIT ELECT 1.0 OF 108 35VDC	
ABC2	0180-0291	CIRCUIT ELECT 1.0 OF 108 35VDC	
ABC3	0180-0121	CIRCUIT EER 0.1 OF 080-208 30VDC	
ABC4	0180-0121	CIRCUIT MICA 200 PF 56	
ABC5	0180-0121	CIRCUIT EER 0.1 OF 080-208 30VDC	
ABC6	0180-0121	CIRCUIT MICA 27 PF 56	
ABC7	0180-0210	CIRCUIT MICA 400 PF 18 30VDC	
ABC8	0180-0121	CIRCUIT EER 0.1 OF 080-208 30VDC	
ABC9	0180-0093	CIRCUIT EER 0.01 OF 080-208 100VDC	
ABC10	0180-0093	CIRCUIT EER 0.01 OF 080-208 100VDC	
ABC11	9100-1660	WIRE/CHUNK 2000 OHM 56	
ABC12	1850-0071	WIRE NPW SELECTED FROM 2837043	
ABC13	1850-0071	WIRE NPW SELECTED FROM 2837043	
ABC14	0800-1015	RESISTOR LUMP 100 OHM 56 1/4W	
ABC15	0800-1015	RESISTOR LUMP 100 OHM 56 1/4W	
ABC16	0800-1015	RESISTOR LUMP 200 OHM 56 1/4W	
ABC17	0800-1015	RESISTOR LUMP 1200 OHM 56 1/4W	
ABC18	0800-1015	RESISTOR LUMP 10K OHM 56 1/4W	
ABC19	0800-1015	RESISTOR LUMP 100K OHM 56 1/4W	
ABC20	0800-1015	RESISTOR LUMP 100K OHM 56 1/4W	
ABC21	0800-0162	CRYSTAL QUARTZ 1.0 MHZ	
	1200-0154	CRYSTAL HOLDER	
AB	05216-2010	BOARD ASSEMBLY UNIT	
	05216-2010	BOARD BLANK PL	
ABC1	0180-0210	CIRCUIT ELECT 3.3 OF 208 35VDC	
ABC2	0180-0229	CIRCUIT EER 0.7-0.25 PF 30VDC	
ABC3	0180-0210	CIRCUIT MICA 10 PF 56	
ABC4	0180-0210	CIRCUIT MICA 10 PF 56	
ABC5	0180-0093	CIRCUIT EER 0.01 OF 080-208 100VDC	
ABC6	0180-0210	CIRCUIT MICA 800 PF 18 30VDC	
ABC7	0180-0229	CIRCUIT ELECT 39 OF 108 35VDC	
ABC8	0180-0210	CIRCUIT ELECT 1.0 OF 108 35VDC	
ABC9	0180-0210	CIRCUIT MICA 10 PF 56	
ABC10	0180-0229	CIRCUIT EER 0.1-0.25 PF 30VDC	
ABC11	0180-0210	CIRCUIT MICA 10 PF 56	
ABC12	0180-0291	CIRCUIT ELECT 1.0 OF 108 35VDC	
ABC13	1901-0040	DIOXIDE SILICON 10MA 5 MW	

# See introduction to this section for ordering information

[illegible]

# See Introduction to this section for ordering information

**Table 6-1. Reference Designation Index (Continued)**

**Table 6-1. Reference Designation Index (Continued)**

Reference Designation	Qty Part No.	Description #	Note
AA1C15	1876-0077	INTIGATED CIRCUITFEEDBACK-DIVIDEM	
AA1C15	1876-0077	INTIGATED CIRCUITFEEDBACK-DIVIDEM	
AA1C16	1876-0077	INTIGATED CIRCUITFEEDBACK-DIVIDEM	
AA1C17	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C18	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C19	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C20	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C21	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C22	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C23	1870-0118	IC15-OUT1 BUFF STORM GATED OUTS	
AA1C24	1870-0119	INTIGATED CIRCUIT	
AA1C25	1870-0119	INTIGATED CIRCUIT	
AA1C26	1870-0119	INTIGATED CIRCUIT	
AA1C27	1870-0119	INTIGATED CIRCUIT	
AA1C28	1870-0119	INTIGATED CIRCUIT	
AA1C29	1870-0119	INTIGATED CIRCUIT	
AA1C30	1820-0110	INTIGATED CIRCUIT	
AA1C31	1820-0110	INTIGATED CIRCUIT	
AA21	1854-0009	U131 NPN	
AA22	1854-0019	U131 NPN	
AA23	1854-0009	U131 NPN	
AA24	1854-0009	U131 NPN	
AA25	1854-0009	U131 NPN	
AA26	1854-0071	U131 NPN(SELECTED FROM 2N3704)	
AA27	1854-0009	U131 NPN	
AA28	1854-0071	U131 NPN(SELECTED FROM 2N3704)	
AA29	1854-0071	U131 NPN(SELECTED FROM 2N3704)	
AA30	1854-0071	U131 NPN(SELECTED FROM 2N3704)	
AA31	1854-0009	U131 NPN	
AA32	1854-0009	U131 NPN	
AA33	1854-0009	U131 NPN	
AA34	1854-0009	U131 NPN	
AA35	1854-0071	U131 NPN(SELECTED FROM 2N3704)	
AA36	1854-0165	U131 NPN	
AA41	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	
AA42	0041-1025	RIPED LUMP 2000 OHM 5% 1/4W	
AA43	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	
AA44	0041-1225	RIPED LUMP 1200 OHM 5% 1/4W	
AA45	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA46	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA47	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA48	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA49	0041-1225	RIPED LUMP 1200 OHM 5% 1/4W	
AA50	0041-1225	RIPED LUMP 1200 OHM 5% 1/4W	
AA51	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA52	0041-1525	RIPED LUMP 1500 OHM 5% 1/4W	
AA53	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	
AA54	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	
AA55	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	
AA56	0041-1025	RIPED LUMP 1000 OHM 5% 1/4W	

\* See introduction to this section for ordering information

Reference Designation	& Part No.	Description #	Note
A0016	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0017	U000-1-1015	RIFLE CUMP 1100 UHM SE 1/4M	
A0018	U000-1-1015	RIFLE CUMP 100A UHM SE 1/4M	
A0019	U000-1-1015	RIFLE CUMP 1100 UHM SE 1/4M	
A0020	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0021	U000-1-1015	RIFLE CUMP 2000 UHM SE 1/4M	
A0022	U000-1-1015	RIFLE CUMP 3000 UHM SE 1/4M	
A0023	U000-1-1015	RIFLE CUMP 51 UHM SA 1/4M	
A0024	U000-1-1015	RIFLE CUMP 2000 UHM SE 1/4M	
A0025	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0026	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0027	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0028	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0029	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0030	U000-1-1015	RIFLE CUMP 27A UHM SE 1/4M	
A0031	U000-1-1015	RIFLE CUMP 470 UHM SE 1/4M	
A0032	U000-1-1015	RIFLE CUMP 470 UHM SE 1/4M	
A0033	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0034	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0035	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0036	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0037	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0038	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0039	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0040	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0041	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0042	U000-1-1015	RIFLE CUMP 10 UHM SE 1/4M	
A0043	U000-1-1015	RIFLE CUMP 470 UHM SE 1/4M	
A0044	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0045	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0046	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0047	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0048	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0049	U000-1-1015	RIFLE CUMP 100 UHM SE 1/4M	
A0050	U000-1-1015	RIFLE CUMP 120K UHM SE 1/4M	
A0051	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0052	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0053	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0054	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0055	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0056	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0057	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0058	U000-1-1015	RIFLE CUMP 10A UHM SE 1/4M	
A0059	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0060	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0061	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0062	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0063	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0064	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0065	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0066	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0067	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0068	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0069	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0070	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0071	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0072	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0073	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0074	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0075	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0076	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0077	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0078	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0079	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0080	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0081	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0082	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0083	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0084	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0085	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0086	U000-1-1015	RIFLE CUMP 1000 UHM SE 1/4M	
A0087	U000-1-1015	RIFLE CUMP	

\* See Introduction to this section for ordering information





Table 6-1. Reference Designation Index (Continued)

Reference Designation	Part No.	Description #	Note
		LAUNCH PANEL	
1	05216-0007	PANEL FRONT	
2	05216-0008	PANEL REAR	
3	05216-0009	SKIN COVER	
4	05216-0010	FRAME ASSEMBLY	
5	05216-0011	LOCKING LATCH	
6	05216-0012	KEYBOARD	
7	05216-0013	HINGE	
8	05216-0014	STANDARD HALF-MODULE	
9	05216-0015	SUBSISTANCE MODULE	
10	05216-0016	CABINET SPACER	
11	05216-0017	FRONT HINGE	
12	05216-0018	WHEEL	

# See Introduction to this section for ordering information

Reference Designation	Part No.	Description #	Note
17	0100-1057	SWITCH/INTERF	
18	0370-0077	ARMATURED BAR FOR 0.250" DIA SHAFT	
19	0101-0092	SWITCH/POWER BUTTON SPST	
20	0101-1234	SWITCH/ILLUM UPDT 0.5A 120VAC/DC	
21	0101-0097	SWITCH/TOGGLE UPDT	
22	0101-0098	SWITCH/TOGGLE SPDT	
23	0101-0103	SWITCH/TOGGLE SPDT	
24	0100-1004	TRANSFORMER	
25	0120-1318	CABLE ASSY/POWER CORD	
26	05216-0007	CABLE/MAIN	
27	05216-0014	CABLE/ASSY/LIGHT	
28	05216-0008	CABLE/REAR INPUT	
29		NOT ASSIGNED	
30	0251-0199	CONNECTOR/PRINTED CIRCUIT 10-CONTACT	
31	0251-0198	CONNECTOR/10-CONTACT	
32	0251-0199	CONNECTOR/2215 CONTACT	
33		NOT ASSIGNED	
34	0251-0194	CONNECTOR/PRINTED CIRCUIT 15-CONTACT	
35		MISCELLANEOUS	
	05216-0001	WINDOW/UNIT DISPLAY	
	05216-0002	CRIMP/CONNECTOR	
	05216-0003	INSERT/CONNECTOR	
	05216-0004	INSERT/REAR UNIT	
	05216-0005	CABLE/COUNTER	
	05216-0006	WINDER/POWER SUPPLY	
	05216-0007	LIGHT/PIPE	
	05216-0008	HINGE	
	0100-0043	STANDARD 11-12 X 1/2	
	0100-0044	HINGE	

# See Introduction to this section for ordering information

Figure 6-1. Cabinet Parts


			
Item No.	Description	HP Part No.	Quantity
1	Front Panel	05216-0002	1
2	Rear Panel	05216-0009	1
3	Side Cover	5000-0702	2
4	Side Frame	5060-0702	2
5	Top Cover	5060-0723	1
6	Bottom Cover	5000-0718	1
7	Hinge	5040-0700	2
8	Tilt Stand	1490-0032	1
9	Foot Assembly	5060-0728	2
10	Spacer	5020-0701	2
11	Window Frame	05216-4004	1
12	Bezel	05216-0003	1

Table 6-2. Replaceable Parts Index

# See Introduction to this section for ordering information

# See introduction to this section for ordering information

Table 6-2. Replaceable Parts Index (Continued)

Part No.	Description #	Mfr.	Mfr. Part No.	TQ
9100-1004	TRANSFORMER	28480	9100-1004	1
9100-0116	LUMINOUS NF 22 UM	28480	9100-0116	1
05216-0001	LASETATTEN SWITCH	28480	05216-0001	1
05216-0002	PANEL PPHUNT	28480	05216-0002	1
05216-0003	METER	28480	05216-0003	1
05216-0009	PANEL REAR	28480	05216-0009	1
05216-0005	CUMM ATTEN SWITCH	28480	05216-0005	1
05216-0006	REAR BLANK PC	28480	05216-0006	1
05216-0004	REAR BLANK PC	28480	05216-0004	1
05216-0010	REAR BLANK PC	28480	05216-0010	1
05216-0012	REAR BLANK PC	28480	05216-0012	1
05216-0013	REAR BLANK PC	28480	05216-0013	1
05216-0001	CASE COUNTER	28480	05216-0001	1
05216-0007	INSERT REAROUT	28480	05216-0007	1
05216-0001	WINDOW	28480	05216-0001	1
05216-0004	FRAME WINDOW	28480	05216-0004	1
05216-0005	LIGHT PIPE	28480	05216-0005	1
05216-0006	MICROPROCESSOR SUPPLY	28480	05216-0006	1
05216-0007	SEMI-CONDUCTOR	28480	05216-0007	1
05216-0008	GROUND CONNECTOR	28480	05216-0008	1
05216-0009	ASSY AMPLIFIER BOARD	28480	05216-0009	1
05216-0004	ASSY DECIMAL BOARD	28480	05216-0004	1
05216-0005	ASSY ATTENUATION SWITCH	28480	05216-0005	1
05216-0007	CABLE MAIN	28480	05216-0007	1
05216-0008	CABLE REAR INPUT	28480	05216-0008	1
05216-0010	OSCILLATION ASSY	28480	05216-0010	1
05216-0012	BOARD ASSY PUMP SUPPLY	28480	05216-0012	1
05216-0013	BOARD ASSY COUNTER	28480	05216-0013	1
05216-0014	CABLE ASSY LIGHT	28480	05216-0014	1
05216-0001	WINDOW UNITS DISPLAY	28480	05216-0001	1

# See Introduction to this section for ordering information

Part No.	Description #	Mfr.	Mfr. Part No.	TQ
1820-0114	INTEGRATED CIRCUIT	28480	1820-0114	7
1820-0114	INTEGRATED CIRCUIT FOR INVERTER	01295	3M-199	1
1820-0412	INTEGRATED CIRCUIT FOR CASE DIVIDER	28480	1820-0412	7
1851-0012	WISSI PNP	04713	2N2904A	1
1851-0015	WISSI PNP	04713	2N2904A-5	2
1851-0014	WISSI PNP SELECTED FROM 2N2904	28480	1851-0014	1
1851-0016	WISSI PNP	04713	2N2904	1
1851-0017	WISSI PNP	04713	2N2904	1
1851-0018	WISSI PNP	04713	2N2904	1
1851-0019	WISSI PNP	04713	2N2904	1
1851-0020	WISSI PNP	04713	2N2904	1
1851-0021	WISSI PNP	04713	2N2904	1
1851-0022	WISSI PNP	04713	2N2904	1
1851-0023	WISSI PNP	04713	2N2904	1
1851-0024	WISSI PNP	04713	2N2904	1
1851-0025	WISSI PNP	04713	2N2904	1
1851-0026	WISSI PNP	04713	2N2904	1
1851-0027	WISSI PNP	04713	2N2904	1
1851-0028	WISSI PNP	04713	2N2904	1
1851-0029	WISSI PNP	04713	2N2904	1
1851-0030	WISSI PNP	04713	2N2904	1
1851-0031	WISSI PNP	04713	2N2904	1
1851-0032	WISSI PNP	04713	2N2904	1
1851-0033	WISSI PNP	04713	2N2904	1
1851-0034	WISSI PNP	04713	2N2904	1
1851-0035	WISSI PNP	04713	2N2904	1
1851-0036	WISSI PNP	04713	2N2904	1
1851-0037	WISSI PNP	04713	2N2904	1
1851-0038	WISSI PNP	04713	2N2904	1
1851-0039	WISSI PNP	04713	2N2904	1
1851-0040	WISSI PNP	04713	2N2904	1
1851-0041	WISSI PNP	04713	2N2904	1
1851-0042	WISSI PNP	04713	2N2904	1
1851-0043	WISSI PNP	04713	2N2904	1
1851-0044	WISSI PNP	04713	2N2904	1
1851-0045	WISSI PNP	04713	2N2904	1
1851-0046	WISSI PNP	04713	2N2904	1
1851-0047	WISSI PNP	04713	2N2904	1
1851-0048	WISSI PNP	04713	2N2904	1
1851-0049	WISSI PNP	04713	2N2904	1
1851-0050	WISSI PNP	04713	2N2904	1
1851-0051	WISSI PNP	04713	2N2904	1
1851-0052	WISSI PNP	04713	2N2904	1
1851-0053	WISSI PNP	04713	2N2904	1
1851-0054	WISSI PNP	04713	2N2904	1
1851-0055	WISSI PNP	04713	2N2904	1
1851-0056	WISSI PNP	04713	2N2904	1
1851-0057	WISSI PNP	04713	2N2904	1
1851-0058	WISSI PNP	04713	2N2904	1
1851-0059	WISSI PNP	04713	2N2904	1
1851-0060	WISSI PNP	04713	2N2904	1
1851-0061	WISSI PNP	04713	2N2904	1
1851-0062	WISSI PNP	04713	2N2904	1
1851-0063	WISSI PNP	04713	2N2904	1
1851-0064	WISSI PNP	04713	2N2904	1
1851-0065	WISSI PNP	04713	2N2904	1
1851-0066	WISSI PNP	04713	2N2904	1
1851-0067	WISSI PNP	04713	2N2904	1
1851-0068	WISSI PNP	04713	2N2904	1
1851-0069	WISSI PNP	04713	2N2904	1
1851-0070	WISSI PNP	04713	2N2904	1
1851-0071	WISSI PNP	04713	2N2904	1
1851-0072	WISSI PNP	04713	2N2904	1
1851-0073	WISSI PNP	04713	2N2904	1
1851-0074	WISSI PNP	04713	2N2904	1
1851-0075	WISSI PNP	04713	2N2904	1
1851-0076	WISSI PNP	04713	2N2904	1
1851-0077	WISSI PNP	04713	2N2904	1
1851-0078	WISSI PNP	04713	2N2904	1
1851-0079	WISSI PNP	04713	2N2904	1
1851-0080	WISSI PNP	04713	2N2904	1
1851-0081	WISSI PNP	04713	2N2904	1
1851-0082	WISSI PNP	04713	2N2904	1
1851-0083	WISSI PNP	04713	2N2904	1
1851-0084	WISSI PNP	04713	2N2904	1
1851-0085	WISSI PNP	04713	2N2904	1
1851-0086	WISSI PNP	04713	2N2904	1
1851-0087	WISSI PNP	04713	2N2904	1
1851-0088	WISSI PNP	04713	2N2904	1
1851-0089	WISSI PNP	04713	2N2904	1
1851-0090	WISSI PNP	04713	2N2904	1
1851-0091	WISSI PNP	04713	2N2904	1
1851-0092	WISSI PNP	04713	2N2904	1
1851-0093	WISSI PNP	04713	2N2904	1
1851-0094	WISSI PNP	04713	2N2904	1
1851-0095	WISSI PNP	04713	2N2904	1
1851-0096	WISSI PNP	04713	2N2904	1
1851-0097	WISSI PNP	04713	2N2904	1
1851-0098	WISSI PNP	04713	2N2904	1
1851-0099	WISSI PNP	04713	2N2904	1
1851-0100	WISSI PNP	04713	2N2904	1
1851-0101	WISSI PNP	04713	2N2904	1
1851-0102	WISSI PNP	04713	2N2904	1
1851-0103	WISSI PNP	04713	2N2904	1
1851-0104	WISSI PNP	04713	2N2904	1
1851-0105	WISSI PNP	04713	2N2904	1
1851-0106	WISSI PNP	04713	2N2904	1
1851-0107	WISSI PNP	04713	2N2904	1
1851-0108	WISSI PNP	04713	2N2904	1
1851-0109	WISSI PNP	04713	2N2904	1
1851-0110	WISSI PNP	04713	2N2904	1
1851-0111	WISSI PNP	04713	2N2904	1
1851-0112	WISSI PNP	04713	2N2904	1
1851-0113	WISSI PNP	04713	2N2904	1
1851-0114	WISSI PNP	04713	2N2904	1
1851-0115	WISSI PNP	04713	2N2904	1
1851-0116	WISSI PNP	04713	2N2904	1
1851-0117	WISSI PNP	04713	2N2904	1
1851-0118	WISSI PNP	04713	2N2904	1
1851-0119	WISSI PNP	04713	2N2904	1
1851-0120	WISSI PNP	04713	2N2904	1
1851-0121	WISSI PNP	04713	2N2904	1
1851-0122	WISSI PNP	04713	2N2904	1
1851-0123	WISSI PNP	04713	2N2904	1
1851-0124	WISSI PNP	04713	2N2904	1
1851-0125	WISSI PNP	04713	2N2904	1
1851-0126	WISSI PNP	04713	2N2904	1
1851-0127	WISSI PNP	04713	2N2904	1
1851-0128	WISSI PNP	04713	2N2904	1
1851-0129	WISSI PNP	04713	2N2904	1
1851-0130	WISSI PNP	04713	2N2904	1
1851-0131	WISSI PNP	04713	2N2904	1
1851-0132	WISSI PNP	04713	2N2904	1
1851-0133	WISSI PNP	04713	2N2904	1
1851-0134	WISSI PNP	04713	2N2904	1
1851-0135	WISSI PNP	04713	2N2904	1
1851-0136	WISSI PNP	04713	2N2904	1
1851-0137	WISSI PNP	04713	2N2904	1
1851-0138	WISSI PNP	04713	2N2904	1
1851-0139	WISSI PNP	04713	2N2904	1
1851-0140	WISSI PNP	04713	2N2904	1
1851-0141	WISSI PNP	04713	2N2904	1
1851-0142	WISSI PNP	04713	2N2904	1
1851-0143	WISSI PNP	04713	2N2904	1
1851-0144	WISSI PNP	04713	2N2904	1
1851-0145	WISSI PNP	04713	2N2904	1
1851-0146	WISSI PNP	04713	2N2904	1
1851-0147	WISSI PNP	04713	2N2904	1
1851-0148	WISSI PNP	04713	2N2904	1
1851-0149	WISSI PNP	04713	2N2904	1
1851-0150	WISSI PNP	04713	2N2904	1
1851-0151	WISSI PNP	04713	2N2904	1
1851-0152	WISSI PNP	04713	2N2904	1
1851-0153	WISSI PNP	04713	2N2904	1
1851-0154	WISSI PNP	04713	2N2904	1
1851-0155	WISSI PNP	04713	2N2904	1
1851-0156	WISSI PNP	04713	2N2904	1
1851-0157	WISSI PNP	04713	2N2904	1
1851-0158	WISSI PNP	04713	2N2904	1
1851-0159	WISSI PNP	04713	2N2904	1
1851-0160	WISSI PNP	04713	2N2904	1
1851-0161	WISSI PNP	04713	2N2904	1
1851-0162	WISSI PNP	04713	2N2904	1
1851-0163	WISSI PNP	04713	2N2904	1
1851-0164	WISSI PNP	04713	2N2904	1
1851-0165	WISSI PNP	04713	2N2904	1
1851-0166	WISSI PNP	04713	2N2904	1
1851-0167	WISSI PNP	04713	2N2904	1
1851-0168	WISSI PNP	04713	2N2904	1
1851-0169	WISSI PNP	04713	2N2904	1
1851-0170	WISSI PNP	04713	2N2904	1
1851-0171	WISSI PNP	04713	2N2904	1
1851-0172	WISSI PNP	04713	2N2904	1
1851-0173	WISSI PNP	04713	2N2904	1
1851-0174	WISSI PNP	04713	2N2904	1
1851-0175	WISSI PNP	04713	2N2904	1
1851-0176	WISSI PNP	04713	2N2904	1
1851-0177	WISSI PNP	04713	2N2904	1
1851-0178	WISSI PNP	04713	2N2904	1
1851-0179	WISSI PNP	04713	2N2904	1
1851-0180	WISSI PNP	04713	2N2904	1
1851-0181	WISSI PNP	04713	2N2904	1
1851-0182	WISSI PNP	04713	2N2904	1
1851-0183	WISSI PNP	04713	2N2904	1
1851-0184	WISSI PNP	04713	2N2904	1
1851-0185	WISSI PNP	04713	2N2904	1
1851-0186	WISSI PNP	04713	2N2904	1
1851-0187	WISSI PNP	04713	2N2904	1
1851-0188	WISSI PNP	04713	2N2904	1
1851-0189	WISSI PNP	04713	2N2904	1
1851-0190	WISSI PNP	04713	2N2904	1
1851-0191	WISSI PNP	04713	2N2904	1
1851-0192	WISSI PNP	04713	2N2904	1
1851-0193	WISSI PNP	04713	2N2904	1
1851-0194	WISSI PNP	04713	2N2904	1
1851-0195	WISSI PNP	04713	2N2904	1
1851-0196	WISSI PNP	04713	2N2904	1
1851-0197	WISSI PNP	04713	2N2904	1
1851-0198	WISSI PNP	04713	2N2904	1
1851-0199	WISSI PNP	04713	2N2904	1
1851-0200	WISSI PNP	04713	2N2904	1
1851-0201	WISSI PNP	04713	2N2904	1
1851-0202	WISSI PNP	04713	2N2904	1
1851-0203	WISSI PNP	04713	2N2904	1
1851-0204	WISSI PNP	04713	2N2904	1
1851-0205	WISSI PNP	04713	2N2904	1
1851-0206	WISSI PNP	04713	2N2904	1
1851-0207	WISSI PNP	04713	2N2904	1
1851-0208	WISSI PNP	04713	2N2904	1
1851-0209	WISSI PNP	04713	2N2904	1
1851-0210	WISSI PNP	04713	2N2904	1
1851-0211	WISSI PNP	04713	2N2904	1
1851-0212	WISSI PNP	04713	2N2904	1
1851-0213	WISSI PNP	04713	2N2904	1
1851-0214	WISSI PNP	04713	2N2904	1
1851-0215	WISSI PNP	04713	2N2904	1
1851-0216	WISSI PNP	04713	2N2904	1
1851-0217	WISSI PNP	04713	2N2904	1
1851-0218	WISSI PNP	04713	2N2904	1
1851-0219	WISSI PNP	04713	2N2904	1
1851-0220	WISSI PNP	04713	2N2904	1
1851-0221	WISSI PNP	04713	2N2904	1
1851-0222	WISSI PNP	04713	2N2904	1
1851-0223	WISSI PNP	04713	2N2904	1
1851-0224	WISSI PNP	04713	2N2904	1
1851-0225	WISSI PNP	04713	2N2904	1
1851-0226	WISSI PNP	04713	2N2904	1
1851-0227	WISSI PNP	04713	2N2904	1
1851-0228	WISSI PNP	04713	2N2904	1
1851-0229	WISSI PNP	04713	2N2904	1
1851-0230	WISSI PNP	04713	2N2904	1
1851-0231	WISSI PNP	04713	2N2904	1
1851-0232	WISSI PNP	04713	2N2904	1
1851-0233	WISSI PNP	04713	2N2904</	

Table 6-3. Code List of Manufacturers

The following code numbers are from the Federal Supply Code for Manufacturers Cataloging Handbook H6-1 (Name in Code) and H6-2 (Code in Name) and their latest supplements. The date of revision and the date of the supplements used appear at the bottom of each page. Alphabetical codes have been arbitrarily assigned to suppliers not appearing in the H6 Handbooks.

Code No.	Manufacturer	Address	Code No.	Manufacturer	Address	Code No.	Manufacturer	Address
00000	U. S. A. Common	Any supplier of U.S.	05347	Ultronix, Inc.	San Mateo, Cal.	11236	CTS of Berne, Inc.	Berne, Ind.
00136	McCoy Electronics	Mount Holly Springs, Pa.	05397	Union Carbide Corp., Elect.		11237	Chicago Telephone of	
00213	Sage Electronics Corp.	Rochester, N. Y.		Div.	New York, N. Y.		California, Inc.	So. Pasadena, Cal.
00287	Cemco, Inc.	Danielson, Conn.	05574	Viking Ind. Inc.	Canoga Park, Cal.	11242	Day State Electronics Corp.	Waltham, Mass.
00314	Humdist	Colton, Calif.	05593	Leuze Electro-Plastics Inc.	Sunnyvale, Cal.	11312	Teledyne Inc., Microwave	
00346	Mictron, Co., Inc.	Valley Stream, N. Y.	05616	Cuomo Plastic (en Electrical			Div.	Palo Alto, Cal.
00373	Carlson Corp.	Cherry Hill, N. J.		Sper. Co.)	Cleveland, Ohio	11314	National Seal	
00656	Aerospace Corp.	New Bedford, Mass.	05624	Harber Colman Co.	Rockford, Ill.	11453	Precision Connector Corp.	Jamaica, N. Y.
00779	Amp. Inc.	Harrisburg, Pa.	05728	Tiffin Optical Co.		11534	Duncan Electronics Inc.	Costa Mesa, Cal.
00781	Aircraft Radio Corp.	Boonton, N. J.			Roslyn Heights, Long Island, N. Y.	11711	General Instrument Corp.	
00809	Crosch, Ltd.	Whitby, Ontario, Canada	05729	Metzco-Trl Corp.	Westbury, N. Y.		Semiconductor Division Products	
00810	Northern Engineering		05783	Stewart Engineering Co.	Santa Cruz, Cal.		Group	Newark, N. J.
	Laboratories, Inc.	Burlington, Wis.	05820	Wakefield Engineering Inc.	Wakefield, Mass.	11717	Imperial Electronic, Inc.	Buena Park, Cal.
00853	Sangamo Electric Co.		06004	Hassick Co., Div. of Stewart		11870	Melabo, Inc.	Palo Alto, Cal.
	Pickens Div.	Pickens, S. C.		Warner Corp.	Bridgeport, Conn.	12136	Philadelphia Handle Co.	Camden, N. J.
00866	Goe Engineering Co.	City of Industry, Cal.	06090	Haychem Corp.	Redwood City, Cal.	12361	Grove Mfg. Co., Inc.	Shady Grove, Pa.
00891	Carl E. Holmes Corp.	Los Angeles, Cal.	06175	Bausch and Lomb Optical		12574	Gulton Ind. Inc., Data System	
00929	Microlab Inc.	Livingston, N. J.		Co.	Rochester, N. Y.		Div.	Albuquerque, N. M.
01002	General Electric Co.		06402	E. T. & Products Co. of		12607	Claronal Mfg. Co.	Dover, N. H.
	Capacitor Dept.	Hudson Falls, N. Y.		Amerita	Chicago, Ill.	12726	Elmar Filter Corp.	W. Haven, Conn.
01009	Alden Products Co.	Brockton, Mass.	06540	Amaton Electronic Hardware		12850	Nippon Electric Co., Ltd.	Tokyo, Japan
01121	Allen Bradley Co.	Milwaukee, Wis.		Co., Inc.	New Rochelle, N. Y.	12881	Melex Electronics Corp.	Clark, N. J.
01255	Litton Industries, Inc.	Beverly Hills, Cal.	06555	Deede Electrical Instrument		12930	Delta Semiconductor Inc.	Newport Beach, Cal.
01281	TRW Semiconductors, Inc.	Laurel, Cal.		Co., Inc.	Penacook, N. H.	12954	Dichson Electronics Corp.	Scottsdale, Arizona
01295	Texas Instruments, Inc.		06666	General Devices Co., Inc.	Indianapolis, Ind.	13019	Aircro Supply Co., Inc.	Wichita, Kansas
	Transistor Products Div.	Dallas, Texas	06751	Components Inc., Ariz. Div.	Phoenix, Arizona	13061	Wilco Products	Detroit, Mich.
01349	The Alliance Mfg. Co.	Alliance, Ohio	06812	Torrington Mfg. Co., West Div.	Van Nuys, Cal.	13103	Thermolloy	Dallas, Texas
01524	Email Parts Inc.	Los Angeles, Cal.	06880	Varian Assoc. Elmar Div.	San Carlos, Cal.	13227	Soltron Devices Inc.	Tappan, N. Y.
01589	Pacific Relays, Inc.	Van Nuys, Cal.	07048	Kelvin Electric Co.	Van Nuys, Cal.	13296	Telefunken (GmbH)	Hannover, Germany
01670	Gudebrod Bros. Bk Co.	New York, N. Y.	07126	Ingtran Co.	Pasadena, Cal.	13835	Midland-Wright Div. of	
01930	Ameruck Corp.	Rockford, Ill.	07137	Transistor Electronics			Pacific Industries, Inc.	Kansas City, Kansas
01960	Pulse Engineering Co.	Santa Clara, Cal.		Corp.	Minneapolis, Minn.	14099	Bem-Tech	Newbury Park, Cal.
02114	Ferroxcube Corp. of		07138	Westinghouse Electric		14192	Calif. Resistor Corp.	Santa Monica, Cal.
	Amerita	Saugerties, N. Y.		Corp., Electronic Tube Div.	Elmira, N. Y.	14284	American Components, Inc.	Coshohocken, Pa.
02116	Wheelock Signals, Inc.	Long Branch, N. J.	07149	Filmohm Corp.	New York, N. Y.	14433	ITT Semiconductor, a Div. of	
02266	Cole Rubber and Plastics Inc.	Sunnyvale, Cal.	07233	Cinch-Graphix Co.	City of Industry, Cal.		Int. Telephone and Telegraph	
02280	Amphenol-Borg Electronics		07256	Silicon Transistor Corp.	Carle Place, N. Y.		Corporation	West Palm Beach, Fla.
	Corp.	Brandsview, Ill.	07281	Avnet Corp.	Culver City, Cal.	14493	Hewlett-Packard Company	Loveland, Colo.
02735	Radio Corp. of America, Semi-		07283	Fairchild Camera & Inst. Corp.		14650	Cumself Dubler Electric Corp.	Newark, N. J.
	conductor and Materials			Semiconductor Div.	Mountain View, Cal.	14674	Corning Glass Works	Corning, N. Y.
	Division	Somerville, N. J.	07322	Minnesota Rubber Co.	Minneapolis, Minn.	14752	Electro Cube Inc.	San Gabriel, Cal.
02771	Vocalite Co. of America,		07387	Bircher Corp. The	Monterey Park, Cal.	14759	William Mfg. Co.	San Jose, Cal.
	Inc.	San Francisco, Conn.		Sylvania Elect. Prod. Inc.		15116	The Sphero Co., Inc.	Little Falls, N. J.
02777	Hughes Engineering Co.	San Fernando, Cal.		Mt. View Operations	Mountain View, Cal.	15253	Webster Electronics Co.	New York, N. Y.
02875	Hudson Tool & Die	Newark, N. J.	07700	Technical Wire Products		15287	Scientific Corp.	Northridge, Cal.
02896	Rylon Molding Corp.	Springfield, N. J.		Inc.	Cranford, N. J.	15291	Adjustable Washing Co.	N. Hollywood, Cal.
03508	G. E. Semiconductor Prod.		07829	Isoline Elect. Co.	Chicago, Ill.	15558	Micron Electronics, Gardn	City, Long Island, N. Y.
	Dept.	Syracuse, N. Y.	07910	Continental Device Corp.	Hawthorne, Cal.	15566	Amprobe Inst. Corp.	Sydney, N. Y.
03705	Apex Machine & Tool Co.	Dayton, Ohio	07933	Raytheon Mfg. Co., Semi-		15631	Cabletronics	Costa Mesa, Cal.
03787	Eldeira Corp.	Compton, Calif.		conductor Div.	Mountain View, Cal.	15772	Twentieth Century Coil	
03818	Parker Seal Co.	Los Angeles, Cal.	07980	Hewlett-Packard Co.			Spring Co.	Santa Clara, Cal.
03877	Transitron Electric Corp.	Wabfield, Mass.		New Jersey Division	Rockaway, N. J.	15801	Fenwal Elect. Inc.	Framingham, Mass.
03880	Profilum Resistor Co.		08145	U. S. Engineering Co.	Los Angeles, Cal.	15818	Amerco Inc.	Mountain View, Cal.
	Inc.	Cedar Knolls, N. J.	08289	Blinn, Delbert Co.	Pomona, Cal.	16037	Spruce Pine Mica Co.	Spruce Pine, N. C.
03954	Dinger Co., Diehl Div.		08358	Burgess Battery Co.		16179	Omni-Spectra Inc.	Detroit, Ill.
	Finderns Plant	Somerville, N. J.			Niagara Falls, Ontario, Canada	16352	Computer Rhode Corp.	Lodi, N. J.
04009	Aeros. Hart and Hegman		08524	Deutch Fastener Corp.	Los Angeles, Cal.	16554	Electroid Co.	Union, N. J.
	Elect. Co.	Hartford, Conn.	08564	Dejatel Co., The	Waterbury, Conn.	16585	Boots Aircraft Nut Corp.	Pasadena, Cal.
04013	Tarvac Corp.	Lambertville, N. J.	08717	Sloan Company	Sun Valley, Cal.	16698	Ideal Prec. Meter Co., Inc.	
04062	Arco Electronic Inc.	Great Neck, N. Y.		ITT Cannon Electric Inc.			De Jur Meter Div.	Brooklyn, N. Y.
04217	Esser Wire	Los Angeles, Cal.		Phoenix Div.	Phoenix, Arizona	16758	Deico Radio Div. of G M Corp.	Kokomo, Ind.
04222	Hi-Q Division of Aeros.	Myrtle Beach, S. C.	08727	National Radio Lab. Inc.	Paramus, N. J.	17109	Thermometrics Inc.	Canoga Park, Cal.
04354	Precision Paper Tube Co.	Wheeling, Ill.	08792	CBS Electronics Semiconductor		17414	Trans Company	Mountain View, Cal.
04404	Palo Alto Division of Hewlett-			Operations, Div. of CBS Inc.	Lowell, Mass.	17675	Hamsi Metal Products Corp.	Akron, Ohio
	Packard Co.	Palo Alto, Cal.	08806	General Electric Co.		17745	Angstrom Prec. Inc.	No. Hollywood, Cal.
04651	Sylvania Electric Products,			Miniature Lamp Dept.	Cleveland, Ohio	17858	Siliconix Inc.	Bennysale, Cal.
	Microwave Device Div.	Mountain View, Cal.	08984	Mel-Rain	Indianapolis, Ind.	17870	McGraw-Edison Co.	Manchester, N. H.
04673	Dakota Engr. Inc.	Culver City, Cal.	09026	Babcock Relays Div.	Costa Mesa, Cal.	18042	Power Design Pacific Inc.	Palo Alto, Cal.
04713	Motorola Inc. Semiconductor		09097	Electronic Enclosures Inc.	Los Angeles, Calif.	18083	Clevip Corp. Semiconductor Div.	Palo Alto, Cal.
	Prod. Div.	Phoenix, Arizona	09134	Texas Capacitor Co.	Houston, Texas	18224	Signifire Corp.	Bannysale, Cal.
04732	Filttron Co., Inc. Western		09145	Tech. Ind. Inc. Alohm		18476	Ty-Car Mfg. Co., Inc.	Holliston, Mass.
	Div.	Culver City, Cal.		Elect.	Durham, Cal.	18486	THW Elect. Comp. Div.	Des Plaines, Ill.
04773	Automatic Electric Co.	Northlake, Ill.	09250	Electro Assemblies, Inc.	Chicago, Ill.	18565	Chomartec	Plainville, Mass.
04796	Sequola Wire Co.	Redwood City, Cal.	09353	C & K Components Inc.	Newton, Mass.	18573	Curtis Instruments Inc.	Mt. Kisco, N. Y.
04811	Precision Coil Spring Co.	El Monte, Cal.	09369	Mallory Battery Co. of		18612	Vishay Instruments Inc.	Milburn, N. J.
04870	P. M. Motor Company	Westchester, Ill.		Canada, Ltd.	Toronto, Ontario, Canada	18813	E. I. DuPont and Chm. Inc.	Wilmington, Del.
04919	Component Mfg. Service		09795	Pennsylvania Fluorocarbon	Elfton Heights, Penn.	18911	Durant Mfg. Co.	Milwaukee, Wis.
	Co.	W. Bridgewater, Mass.	09922	Burndy Corp.	Norwalk, Conn.	19315	The Hendix Corp., Navigation &	
65006	Twentieth Century Plastics,		10214	General Transistor Western			Control Div.	Teterboro, N. J.
	Inc.	Los Angeles, Cal.		Corp.	Los Angeles, Cal.	19500	Thomas A. Edison Industries,	
05277	Westinghouse Electric Corp.		10411	Ti-Tal, Inc.	Berkeley, Cal.		Div. of McGraw-Edison	West Orange, N. J.
	Semiconductor Dept.	Youngwood, Pa.	10646	Carborandum Co.	Niagara Falls, N. Y.	19589	Concoa	Palden Park, Cal.

00015-49  
Revised: May, 1970

From: Handbook Supplements  
H6-1 Dated January 1970

Table 6-3. Code List of Manufacturers (Continued)

Code No	Manufacturer	Address	Code No	Manufacturer	Address	Code No	Manufacturer	Address
19644	IBC Electronics	Hornbeards, N. Y.	71492	C. P. Clare & Co.	Chicago, Ill.	78452	Thompson-Premier & Co.	Chicago, Ill.
19701	Electra Mfg. Co.	Independence, Kansas	71590	Centralab Div. of		78471	Tillys Mfg. Co.	San Francisco, Cal.
20183	General Airplane Corp.	Philadelphia, Pa.		Globe Union Inc.	Milwaukee, Wis.	78488	Stackpole Carbon Co.	St. Marys, Pa.
21226	Excelsior, Inc.	Long Island City, N. Y.	71616	Commercial Plastics Co.	Chicago, Ill.	78493	Standard Thompson Corp.	Waltham, Mass.
21335	Fabur Bearing Co., The	New Britain, Conn.	71700	Cornish Wire Co., The	New York, N. Y.	78553	Tennant Products, Inc.	Cleveland, Ohio
21320	Federal Metallurgical Corp.	N. Chicago, Ill.	71707	Choi Coil Co., Inc.	Providence, R. I.	78590	Transducer Engineers	San Gabriel, Cal.
22020	General Radio Co.	Mechelen, N. J.	71744	Chicago Miniature Lamp Works	Chicago, Ill.	78747	Uemite Co.	Newbury, Mass.
22042	Texcon Corp.	Indianapolis, Ind.	71785	Cluck Mfg. Co.		79136	Walden Kohnen Inc.	Long Island City, N. Y.
22783	British Radio Electronics Ltd.	Washington, D.C.		Howard B. Jones Div.	Chicago, Ill.	79142	Verder Inc. Inc.	Hartford, Conn.
24455	G. E. Lamp Division, Nela Park	Cleveland, Ohio	71984	Dow Corning Corp.	Mt. Pleasant, Mich.	79251	Wenco Mfg. Co.	Chicago, Ill.
24655	General Radio Co.	West Concord, Mass.	72136	Electric Mfg. Mfg. Co., Inc.		79727	Continental-Walt Electronics Corp.	Philadelphia, Pa.
24681	Memorex Inc., Comp. Div.	Huntington Ind.			Williamstown, Conn.			
26365	Gates Reproducer Corp.	New Rochelle, N. Y.	72139	Dialight Corp.	Brooklyn, N. Y.	79963	Zurick Mfg. Corp.	New Rochelle, N. Y.
26462	Grubert Title Co. of America, Inc.	Carlstadt, N. J.	72756	Indiana General Corp.		80021	Mopco Division of Seawood Clock Co.	Morrisstown, N. J.
26651	Compuce Hollister Co.	Hollister, Cal.		Electronics Div.	Kearny, N. J.	80623	Presidio Corp.	Tulso, Okla.
26992	Hamilton Watch Co.	Lancaster, Pa.	72819	General Instrument Corp.		80720	Schultz Alloy Products Co.	Elizabeth, N. J.
28480	Hewlett-Packard Co.	Palo Alto, Cal.		Cap Division	Newark, N. J.	80731	Electronic Industries Association	
28520	Heyman Mfg. Co.	Kensington, N. J.	72795	Drake Mfg. Co.	Harwood Heights, Ill.		Standard Sales of semiconductor devices	
30617	Instrument of Specialists Co.		72825	Hugh H. Fly Inc.	Philadelphia, Pa.		ans manufacturer	
	Inc.	Little Falls, N. J.	72928	Guleman Co.	Chicago, Ill.	80707	Thomas Seitch, Div. Mason Electronics	
31173	G. E. Receiving Tube Dept.	Darnsbury, Ky.	72992	Elastic Stop Nut Corp.	Union, N. J.		Corp.	Wallingford, Conn.
35434	Leffstrom Inc.	Chicago, Ill.	72964	Robert M. Hadley Co.	Los Angeles, Cal.	80221	United Transformer Corp.	New York, N. Y.
36196	Stanpak Cell Products		72992	Erie Technological Products, Inc.	Erie, Pa.	80248	United Electric Corp.	Chicago, Ill.
	Ltd.	Markham, Ontario, Canada	73011	Hanson Mfg. Co., Inc.	Providence, Ind.	80294	Varco Inc.	Diverside, Cal.
36287	Cunningham, W. H. & Hill		73076	H. M. Harper Co.	Chicago, Ill.	80411	Arco Div. of H. H. Harshaw Controls Co.	
	Ltd.	Toronto, Ontario, Canada	73136	Helipot Div. of Beckman Inst., Inc.	Fullerton, Cal.			
37942	P. R. Mallory & Co., Inc.	Indianapolis, Ind.	73293	Hughes Products Division of		80466	All Star Products Inc.	Columbus, Ohio
39541	Mechanical Industries Prod. Co.	Akron, Ohio		Hughes Aircraft Co.	Newport Beach, Cal.	80509	Avery Label Co.	Monrovia, Cal.
40920	Miniature Precision Bearings, Inc.	Kearny, N. J.	73445	Amperelect Corp.	Hicksville, L. I., N. Y.	80583	Hammilland Co., Inc.	Mary Hill, N. C.
40931	Minneapolis Inc.	Minneapolis, Minn.	73506	Drath's Semiconductor Corp.		80640	Stevens, Arnold, Co., Inc.	Woburn, Mass.
42190	Meter Co.	Chicago, Ill.			New Haven, Conn.	80640	Stevens, Arnold, Co., Inc.	Woburn, Mass.
43990	C. A. Nierren Co.	Englewood, Colo.	73549	Carlisle Electric, Inc.	Hartford, Conn.	80650	Stevens, Arnold, Co., Inc.	Woburn, Mass.
44655	Omrite Mfg. Co.	Stokie, Ill.	73586	Circle E. Mfg. Co.	Trenton, N. J.	80650	Stevens, Arnold, Co., Inc.	Woburn, Mass.
46384	Penn Eng. & Mfg. Corp.	Douglas, Pa.	73682	George K. Garrett Co.		80673	Stevens, Arnold, Co., Inc.	Woburn, Mass.
47904	Polaroid Corp.	Cambridge, Mass.			Philadelphia, Pa.	80695	Tra Transformer Corp.	Yonkers, N. Y.
49620	Precision Thermometer & Inst. Co.	Southampton, Pa.	73724	General Electric Products, Inc.	Chicago, Ill.	81212	Winchester Elec. Div. Eaton Ind. Inc.	Dakota, Conn.
49956	Microvac & Power Tube Div.	Waltham, Mass.	73743	General Electric Products, Inc.	Cincinnati, Ohio			
50900	Rovan Control Co.	Westminster, Md.	73793	General Industries Co., The	Elkhart, Ohio	81349	Military Specification	
52983	HP Co. Mod. Elec. Div.	Waltham, Mass.	73846	Goshen Sampling & Tool Co.	Goshen, Ind.	81443	International Rectifier Corp.	El Segundo, Cal.
54294	Hallbrook Mfg. Co.	Selma, N. C.	73899	JED Electronics Corp.	Brooklyn, N. Y.	81541	Amplex Electronics, Inc.	Cambridge, Maryland
55026	Simpson Electric Co.	Chicago, Ill.	73905	Jennings Radio Mfg. Corp.	San Jose, Cal.	81600	Barry Controls, Div. Barry Wright Corp.	Watertown, Mass.
55933	Sonotone Corp.	Elmsford, N. Y.	73957	Groves Div. Corp.	Rockfield, N. J.	82042	Carver Precision Electric Co.	Stokie, Ill.
55938	Raytheon Co. Commercial Apparatus & System Div.	So. Norwalk, Conn.	74276	Signalite Inc.	Neptune, N. J.	82043	North Faraday Inc., Copper Box	Hoboken, N. J.
56133	Spaulding Filter Co., Inc.	Tonawanda, N. Y.	74455	J. H. Vinton, and Sons	Winchester, Mass.	82116	Electric Regulator Corp.	Newark, Conn.
56249	Sprague Electric Co.	North Adams, Mass.	74461	Industrial Condenser Corp.	Chicago, Ill.	82142	Jeffers Electronics Division of	
56474	Superior Elec. Co.	Brush, Conn.	74608	R. F. Products Division of			Spear Carbon Co.	Do " Pa.
56486	Tela Corp.	Tulsa, Okla.		Amphenol-Berry Electronic Corp.		82170	Fairchild Camera & Inst. Corp.	Paramus, N. J.
56730	Thomas & Betts Co.	Elizabeth, N. J.	74970	E. F. Johnson Co.	Waukegan, Minn.		Space & Defense Systems Div.	Paramus, N. J.
57042	Trigitt Electrical Inst. Co.	Bluffton, Ohio	75042	International Resistance Co.	Philadelphia, Pa.	82260	Magnum Industries, Inc.	Greenwich, Conn.
61175	Union Switch and Signal Div. of		75263	Kevonite Carbon Co., Inc.	St. Marys, Pa.	82219	Sylvania Electric Prod., Inc.	Enghart, Pa.
	Westinghouse Air Brake Co.	Pittsburgh, Pa.	75378	C/S Knights, Inc.	Norfolk, Ill.		Electronic Tube Division	
62119	Universal Electric Co.	Duquesne, Mich.	75382	Kulka Electric Corp.	Mt. Vernon, N. Y.	82376	Astron Corp.	East Newark, Harrison, N. J.
63743	Ward-Leonard Electric Co.	Mt. Vernon, N. Y.	75818	Lenz Electric Mfg. Co.	Chicago, Ill.	82389	Switchcraft, Inc.	Chicago, Ill.
64959	Western Electric Co., Inc.	New York, N. Y.	75915	Littell, Inc.	Des Plaines, Ill.	82447	Metals & Controls Inc.	
65092	Western Inst. Inc. Western-Newark	Newark, N. J.	76005	Lord Mfg. Co.	Erie, Pa.		Research Products	Attleboro, Mass.
66295	Wittek Mfg. Co.	Chicago, Ill.	76210	C. W. Marvel	San Francisco, Cal.	82708	Phillips Advance Control Co.	John, Ill.
68246	Minnesota Mining & Mfg. Co.		76433	General Instrument Corp.		82806	Research Products Corp.	Malvern, Wis.
	Revere-Minnom Div.	St. Paul, Minn.		Micamold Division	Newark, N. J.	82877	Reform Mfg. Co., Inc.	Woodstock, N. Y.
70276	Allen Mfg. Co.	Hartford, Conn.	76487	James Millen Mfg. Co., Inc.	Malton, Mass.	82993	Vector Electronics Co.	Glendale, Cal.
70309	Allied Control	New York, N. Y.	76493	J. W. Miller Co.	Los Angeles, Cal.	83078	Carr Fastener Co.	Cambridge, Mass.
70318	Allmetal Screw Product Co., Inc.		76530	Cinch-Monadnock, Div. of United Carr		83096	New Hampshire Ball Bearing, Inc.	Dorchester, N. H.
		Garden City, N. Y.		Fastener Corp.	San Leandro, Cal.			
70417	Amplex, Div. of Chrysler Corp.	Detroit, Mich.	76545	Murphy Electric Co.	Cleveland, Ohio	83125	General Instrument Corp.	Darlington, S. C.
70485	Atlantic India Rubber Works, Inc.	Chicago, Ill.	76703	National Union	Newark, N. J.	83146	ITT Wire and Cable Div.	Los Angeles, Cal.
70583	Amperelect Co., Inc.	Union City, N. J.	76854	Oak Manufacturing Co.	Crystal Lake, Ill.	83186	Victory Eng. Corp.	Springfield, N. J.
70674	ADC Products Inc.	Minneapolis, Minn.	77008	The Pandex Corp.		83296	Booth Corp., Red Bank Div.	Red Bank, N. J.
70903	Belden Mfg. Co.	Chicago, Ill.		Electronics Div.	San Diego, Cal.	83215	Hedley Corp.	Moline, Ill.
70998	Bird Electric Corp.	Chicago, Ill.	77075	Parline Metals Co.	San Francisco, Cal.	83224	Roman Inc.	Newport Beach, Cal.
71002	Birchbach Radio Co.	New York, N. Y.	77221	Phonatron Instrument and Electronic Co.	So. Pasadena, Cal.	83330	Smith, Herman H., Inc.	Brooklyn, N. Y.
71034	Bulley Electric Co., Inc.	Erie, Pa.	77262	Philadelphia Steel and Wire Corp.	Philadelphia, Pa.	83332	Tech Lab	Palmaden Park, N. J.
71041	Boston Gear Works Div. of					83365	Central Wire Co.	Chicago, Ill.
	Murray Co. of Texas	Quincy, Mass.	77342	American Machine & Foundry Co.	Princeton, Ind.	83501	Gavit Wire and Cable Co., Div. of	Brookfield, Mass.
71218	Bul Radio, Inc.	Willoughby, Ohio		Peter & Drumfield Div.			Aeracore Corp.	
71270	Cambridge Thermionics Corp.	Cambridge, Mass.	77630	TIW Electronic Components Div.	Camden, N. J.	83594	Borroughs Corp., Electronics	Plainfield, N. J.
71286	Camloc Fastener Corp.	Paramus, N. J.	77638	General Instrument Corp.	Brooklyn, N. Y.		Tube Div.	
71313	Cardwell Condenser Corp.		77764	Resistance Products Co.	Harrisburg, Pa.	83740	Union Carbide Corp., Consumer	New York, N. Y.
		Lindenhurst, L. I., N. Y.	77910	Robinson Corp. of Calif	Torrance, Cal.		Prod. Div.	
71400	Bussman Mfg. Div. of		78189	Shabazz Dist. of		83777	Model Eng. and Mfg. Inc.	Huntington, Ind.
	McGraw-Edison Co.	St. Louis, Mo.		Illinois Tool Works	Elgin, Ill.	83821	Lloyd Scruggs Co.	Fenton, Mo.
71436	Chicago Condenser Corp.	Chicago, Ill.	78271	Sigma	So. Braintree, Mass.	83942	Acron Electronics Inc. & Radio Co.	Indi, N. J.
71447	Calif. Spring Co., Inc.	Pico-Rivera, Cal.	78283	Signal Indicator Corp.	New York, N. Y.	84173	Arco Electronics Inc.	Great Neck, N. Y.
71450	CTS Corp.	Elkhart, Ind.	78290	Strubers-Dunn Inc.	Pittman, N. J.	84296	A. J. Shoenberger Co., Inc.	San Francisco, Cal.
71468	ITT Cannon Electric Inc.	Los Angeles, Cal.				84413	TIW Capacitor Div.	Oyallia, Neb.
71471	Cinema, Div. Arroyo Corp.	Burbank, Cal.						

00015-49  
Revised May, 1970From Handbook Supplements  
H4-1 Dated January 1970

Table 6-3. Code List of Manufacturers (Continued)

Code No.	Manufacturer	Address	Code No.	Manufacturer	Address	Code No.	Manufacturer	Address
84870	Sarkis Tazian, Inc.	Bloomington, Ind.	91029	Honeywell Inc., Micro Switch Division	Freeport, Ill.	96095	Hi-Q Div. of Arcon Corp.	Orlean, N.Y.
85484	Boonton Molding Company	Boonton, N.J.	91961	Nahm-Bros. Spring Co.	Oakland, Cal.	96256	Thorndarson-Meissner Inc.	St. Carmel, Ill.
85471	A. B. Boyd Co.	San Francisco, Cal.	92180	Tru-Connector Corp.	Peabody, Mass.	96296	Solar Mfg. Co.	Los Angeles, Cal.
85474	R. M. Bramante & Co.	San Francisco, Cal.	92267	Elmer Optical Co., Inc.	Rochester, N.Y.	96396	Microwatch, Div. of	Freeport, Ill.
85660	Kolled Korda, Inc.	Hamden, Conn.	92702	IMC Magnetics Corp.	Westbury, L.I., N.Y.	96330	Callison Series Co.	Chicago, Ill.
85811	Seamless Rubber Co.	Chicago, Ill.	92966	Hudson Lamp Co.	Kearney, N.J.	96341	Microwave Associates, Inc.	Burlington, Mass.
86174	Fairair Bearing Co.	Los Angeles, Calif.	93332	Sylvania Electric Prod. Inc.	Woburn, Mass.	96351	Excel Transformer Co.	Oakland, Cal.
86197	Clifton Precision Products Co., Inc.	Clifton Heights, Pa.	93360	Holburn & Myers Inc.	Pittsford Park, N.J.	96356	Xcelite, Inc.	Orchard Park, N.Y.
86579	Precision Rubber Products Corp.	Dayton, Ohio	93410	Items Controls, Div. of Kase	Manfield, Ohio	96711	San Fernando Elec. Mfg. Co.	San Fernando, Cal.
86684	Radio Corp. of America, Electronic Comp. & Devices Division	Harrison, N.J.	93632	Water Mfg. Co.	Colver City, Cal.	96881	Thomson Ind. Inc.	Long Island, N.Y.
86928	Swastron Mfg. Co.	Glendale, Cal.	93929	G.V. Controls	Livingston, N.J.	97464	Industrial Retaining Ring Co.	Irvine, N.J.
87034	Marro Industries	Anaheim, Cal.	94137	General Cable Corp.	Bayonne, N.J.	97529	Automatic & Precision Mfg.	Englewood, N.J.
87216	Philco Corporation (Lansdale Division)	Lansdale, Pa.	94144	Raytheon Co., Comp. Div.	Quincy, Mass.	97579	Reon Distributor Corp.	Yonkers, N.Y.
87473	Western Fibrous Glass Products Co.	San Francisco, Cal.	94148	Scientific Electronics Products, Inc.	Loveland, Colo.	97983	Little System Inc., Adler Western Common. Div.	New Rochelle, N.Y.
87664	Van Waters & Rogers Inc.	San Francisco, Cal.	94154	Wagner Elect. Corp.	Newark, N.J.	98141	R-Tronics, Inc.	Jamaica, N.Y.
87930	Tower Mfg. Corp.	Providence, R.I.	94197	Curtiss-Wright Corp., Electronics Div.	East Paterson, N.J.	98159	Rubber Tech, Inc.	Gardena, Cal.
88140	Cutler-Hammer, Inc.	Lisle, Ill.	94222	South Chester Corp.	Chester, Pa.	98220	Hewlett-Packard Co., Medical Elec. Div.	Pasadena, Cal.
88220	Gould-National Batteries, Inc.	St. Paul, Minn.	94310	Wire Cloth Products, Inc.	Bellaire, Ill.	98276	Microlit, Inc.	So. Pasadena, Cal.
88688	General Mills, Inc.	Bellville, N.Y.	94375	Automatic Metal Products Co.	Brooklyn, N.Y.	98291	Sealstro Corp.	Mamaroneck, N.Y.
89231	Graybar Electric Co.	Oakland, Cal.	94692	Worcester Pressed Aluminum Corp.	Worcester, Mass.	98376	Zero Mfg. Co.	Durham, Cal.
89473	G.E. Distributing Corp.	Schenectady, N.Y.	94696	Magnetall Electric Co.	Chicago, Ill.	98410	Etc. Inc.	Cleveland, Ohio
89479	Security Co.	Detroit, Mich.	95023	George A. Philbrick Researches, Inc.	Boston, Mass.	98731	General Mills Inc., Electronics Div.	Minneapolis, Minn.
89665	United Transformer Co.	Chicago, Ill.	95146	Alco Elect. Mfg. Co.	Lawrence, Mass.	98724	Pasco Division of Hewlett-Packard Co.	Palo Alto, Cal.
90010	United Shoe Machinery Corp.	Beverly, Mass.	95236	Alphas Products Corp.	Dania, Fla.	98821	North Hills Electronics, Inc.	Glen Cove, N.Y.
90179	U.S. Rubber Co., Consumer Ind. & Plastic Prod. Div.	Pasadena, N.J.	95236	Continental Connector Corp.	Woburn, N.Y.	98878	International Electronic Research Corp.	Burbank, Cal.
90365	Bellefonte Specialty Tool Mfg., Inc.	Bellefonte, Ill.	95263	Everett Mfg. Co., Inc.	Long Island, N.Y.	99109	Columbia Technical Corp.	New York, N.Y.
90763	United Carr Fastener Corp.	Chicago, Ill.	95268	National Coil Co.	Sheridan, Wyo.	99312	Varian Associates	Palo Alto, Cal.
90970	Bearing Engineering Co.	San Francisco, Cal.	95275	Vitramon, Inc.	Bridgport, Conn.	99376	Allen Corp.	Winchester, Mass.
91146	ITT Cannon Elect. Inc.	Salem, Mass.	95348	Gordon Corp.	Bloomfield, N.J.	99515	Marshall Ind., Capable Div.	Meriden, Cal.
91260	Connor Spring Mfg. Co.	San Francisco, Cal.	95354	Melrose Mfg. Co.	Belling Meadows, Ill.	99707	Control Switch Division, Controls Co. of America	El Segundo, Cal.
91345	Miller Dial & Nameplate Co.	El Monte, Cal.	95566	Arnold Engineering Co.	Marengo, Ill.	99800	Dehavan Electronics Corp.	East Aurora, N.Y.
91418	Radio Materials Co.	Chicago, Ill.	95712	Dac Acoustic Co., Inc.	Franklin, Ind.	99848	Wilco Corporation	Indianapolis, Ind.
91506	Augat Inc.	Attleboro, Mass.	95884	Keaton Mfg. Co.	Wayne, Ill.	99928	Brannos Corp.	Whippany, N.J.
91637	Dale Electronics, Inc.	Columbus, Nohr	95887	Arckesser Co.	Chicago, Ill.	99934	Pennbrant, Inc.	Boston, Mass.
91662	Kico Corp.	Willow Grove, Pa.	97777	Microwave Assoc., West, Inc.	Sunnyvale, Cal.	99942	Holmas Electronics Corp.	San Francisco, Cal.
91673	Epiphone Inc.	New York, N.Y.				99957	Testology Instrument Corp. of California	El Monte, Cal.
91737	Greiner Mfg. Co., Inc.	Waukegan, Ill.						
91827	K.F. Development Co.	Redwood City, Cal.						
91886	Malco Mfg., Inc.	Chicago, Ill.						

The following HP Vendors have no number assigned in the latest supplement to the Federal Supply Code for Manufacturers Handbook

0000F	Malco Tool and Die	Los Angeles, Calif.	000CS	Hewlett-Packard Co., Colorado Springs Div.	Colorado Springs, Colorado	000QQ	Cochran	Oakland, Cal.
0000Z	Willow Leather Products Corp.	Newark, N.J.	000MM	Rubber Eng. & Development	Hayward, Cal.	000WW	California Eastern Lab.	Berkeley, Cal.
000AB	ETA	England	000SN	A "N" D Mfg. Co.	San Jose, Cal.	000YY	S. K. Smith Co.	Los Angeles, Cal.
000BB	Precision Instrument Comp. Co.	Van Nuys, Cal.						



# BACK DATING MANUAL CHANGES

## SECTION VII

### MANUAL CHANGES

#### 7-1. CURRENT INSTRUMENTS

7-2. This manual applies directly to Model 5216A Electronic Counters with serial prefix number 1040A (refer to Paragraph 1-7).

#### 7-3. NEWER INSTRUMENTS

7-4. As changes are made, newer instruments may have serial numbers not listed in this manual. The manuals for these instruments will be supplied with an additional "Manual Changes" sheet containing the required information; contact your nearest Hewlett-Packard Sales and Service office for information if this sheet is missing.

#### 7-5. OLDER INSTRUMENTS

7-6. This manual with the changes listed in Table 7-1 also applies to 5216A Electronic Counters having serial prefix numbers 076- and below.

Table 7-1. Back-dating Manual Changes

SERIAL PREFIX	MAKE MANUAL CHANGE
076-	1
040-	1, 2
016-	1, 2, 3
748-	1, 2, 3, 4
744-	1, 2, 3, 4, 5
712-, 716	1, 2, 3, 4, 5, 6

#### CHANGE 1

Page 1-1, Table 1-1:

Change detachable power cord Part No. to 8120-0078

Page 6-5, Table 6-1:

Change F1 2110-0033 to 2110-0018  
J7 1251-2357 to 1251-0148

Page 6-6, Table 6-1:

Change S4 3101-1234 to 3101-0033  
W1 8120-1348 to 8120-0078

Page 6-7, Figure 6-1:

Change Rear Panel Part No. to 05216-0004

Page 6-8, Table 6-2:

Change 1251-2357 to 1251-0148; Mfr. No. to 87930; Mfr. Part No. to 1005-1

Page 6-9, Table 6-2:

Change 8120-1348 to 8120-0078; Mfr. No. to 28480; Mfr. Part No. 8120-0078

Change 05216-0009 to 05216-0004; Mfr. Part No. to 05216-0004

Page 8-27, Figure 8-11:

Use primary power supply schematic marked "PRE-IEC PRIMARY POWER SUPPLY"

CHANGE 2:

Table 6-1:

Delete A4-05216-6013 Main Board Assembly and all lines prefixed by A4; replace with Table 7-2, A4-05216-6011 Main Board Assembly.

Delete A6-05216-6012 Power Supply Assembly and all lines prefixed by A6; replace with Table 7-3, A6-05216-6002 Power Supply Assembly.

Delete W3-05216-6014 Cable, Gate Light.

Change T1 from 9100-3004 Transformer to 9100-2438.

Delete A1C7 0150-0050 C:FXD 1000 pf.

Change A1R6 from 0683-1035 R:FXD 10K ohm to 0684-1011 R:FXD 100 ohm 5% 1/4W.

Change A1R8 from 0683-1035 R:FXD 10K ohm to 0683-2025 R:FXD 2K ohm 5% 1/4W.

Change A1CR1 and A1CR2 from 190'-0050 Diode to 1910-0016 Diode Germanium 60WIV.

Delete Figures 8-3, 8-4, 8-5, 8-6, 8-7, 8-9, and 8-10 (sheets 1, 2, and 3), and 8-11. (Note: Figures 8-3, 8-4, 8-5, and 8-6 will not be replaced.)

Replace Figures 8-7, 8-9, 8-10, and 8-11 with Figures 7-1, 7-2, 7-3, 7-4, 7-5, and 7-6.

Page 7-5, Table 7-2:

Change A4IC35 to 1820-0117 Circuit HP.

CHANGE 3:

Table 7-2:

Add A4C5 0140-0221 C:FXD MICA 220 pf 1%

Add A4CR10 1910-0016 Diode:Germanium 100 MA

Delete Figure 7-3. Replace with Figure 7-7.

CHANGE 4:

Page 5-1, Table 5-1:

Change A3 to 10 MHz oscillator 05216-6006

Change A4 to Main Board 05216-6001

Page 5-5, Table 5-3:

Change TIME BASE to read as follows:

TIME BASE

1. TIME BASE FREQUENCY: 10 MHz

STABILITY: Aging Rate: less than  $\pm 2 \times 10^{-6}$ /month  
Temperature: less than  $\pm 1 \times 10^{-5}$  from  $+15^{\circ}\text{C}$  to  $+35^{\circ}\text{C}$   
less than  $\pm 3 \times 10^{-5}$  from  $0^{\circ}\text{C}$  to  $+50^{\circ}\text{C}$   
Line Voltage: less than  $1 \times 10^{-6}$  for  $\pm 10\%$  change

- Connect output of Counter FREQ STD jack to Oscilloscope vertical input.
- Trigger Oscilloscope externally with a 1 MHz signal from a standard frequency source.
- Set Oscilloscope sweep time to  $1 \mu\text{s}/\text{cm}$ .
- Horizontal drift of Oscilloscope in cm./sec is difference between standard frequency and counter time base frequency in parts in  $10^6$ .

## CHANGE 4 (Continued):

## Page 5-5, Table 5-3 (Continued)

- e. Record frequency difference. For long term stability, this test should be made daily for a period of one month.

NOTE: Temperature must be kept constant, or compensation for temperature difference must be made whenever a frequency difference is recorded. Unless a record of the temperature and date of last calibration is available, the frequency offset should not be considered drift or aging rate of the 10 MHz crystal.

- f. Vary line voltage  $\pm 10\%$  and record frequency difference on test card.

NOTE: Stability as a function of temperature may be checked by performing steps g and h.

- g. Vary operating temperature from  $+15^{\circ}\text{C}$  to  $+35^{\circ}\text{C}$  and record frequency difference.
- h. Vary operating temperature from  $0^{\circ}\text{C}$  to  $+50^{\circ}\text{C}$  and record frequency difference.

## Page 5-8a-b, PERFORMANCE CHECK TEST CARD:

Change TIME BASE FREQUENCY to read as follows:

TIME BASE FREQUENCY: 10 MHz

1. Stability: Aging Rate: less than $\pm 2 \times 10^{-6}/\text{month}$	less than $\pm 2 \times 10^{-6}/\text{mo.}$
Temperature: less than $\pm 1 \times 10^{-5}$	
from $+15^{\circ}\text{C}$ to $+35^{\circ}\text{C}$	less than $\pm 1 \times 10^{-5}$
less than $\pm 3 \times 10^{-5}$	
from $0^{\circ}\text{C}$ to $+50^{\circ}\text{C}$	less than $\pm 3 \times 10^{-5}$
Line Voltage: less than $1 \times 10^{-6}$	
for $\pm 10\%$ change	less than $1 \times 10^{-6}$

## Table 6-1:

Delete A3-05216-6010 Oscillator Assembly and all lines refixed by A3; replace with Table 7-4, A3-05216-6006 Oscillator Assembly.

## Table 7-2:

Change A4-05216-6013 to 0521C-6001

Change 05216-2013 to 05216-2001

Add A4C3 0160-0168 C:FXD MY 0.1UF 10% 200VDCW.

Change A4CR26, A4CR27 to 1902-3404 Diode:Zener.

Change A4IC1, A4IC2, A4IC3, A4IC4, A4IC5, A5IC6, A4IC7, A4IC8 to 1820-0098 Circuit: Integrated.

Change A4R1, A4R2, A4R3, A4R4 to 0675-1021 R:FXD Carbon 1000 ohm 10% 1/8W.

Change A4R5 to 0683-1025 R:FXD COMP 1000 ohm 5% 1/4W.

Change A4R6 to 0675-1021 R:FXD Carbon 1000 ohm 10% 1/8W.

Change A4R10 to 0683-6815 R:FXD COMP 680 ohm 5% 1/4W.

Change A4R12 to 0608-5103 R:FXD COMP 530 ohm 5% 1/8W.

Replace Figures 7-2, 7-4, and 7-7 with Figures 7-9, 7-10, and 7-11.

Replace Figure 8-6 with Figure 7-12.

Change A4IC35 to 1820-0254\* Circuit HP.

\*1820-0254 is replacement part for 1820-0079 and when used A4R42 must be changed to 51 ohms. Hence, change A4R42 to 0683-5105 51 OHM when this IC replacement is made.

CHANGE 5:

Figure 7-1:

Change A1R3 from 2000 ohms to 10K ohms.

Delete A1CR1 and A1CR2.

Table 6-1:

Change A1R8 to 0683-1035 R:FXD COMP 10K ohms 5% 1/4W.

Delete A1CR1 and A1CR2 (not assigned)

CHANGE 6:

Figure 7-8:

Change A4R10 from 680 ohms to 470 ohms

Figure 7-9:

Delete CR1 between XA4(1) and XA4(15).

Delete CR2 in parallel with DS1 (GATE light).

Figure 7-3:

Change A6R3 from 220 ohms to 430 ohms.

Table 7-2:

Change A4R10 to 0683-4715 R:FXD COMP 470 ohm 5% 1/4W.

Table 7-3:

Change A6CR13 to 1902-3193 Diode, SII 13.3V

Change A6R3 to 0683-4315 R:FXD COMP 430 ohm 5% 1/4W.

Table 6-1:

Delete CR1 and CR2.

02430-3

Reference Designation	Part No.	Description #
AN	05210-6011	MAIN BOARD ASSY
ANCI	05216-2011	BUKIDBLANK PC
	0150-0042	CIRCUIT 11 5.1 PF 5% 500VDCW
ANCI2	0150-0093	CIRCUIT 12 0.01 UF 500-200 100VDCW
ANCI3		NOT ASSIGNED
ANCI4	0150-2209	CIRCUIT 13 10% PF 5%
ANCI5		NOT ASSIGNED
ANCI6	0150-0229	CIRCUIT 14 10% PF 100VDCW
ANCI7	0150-0291	CIRCUIT 15 10% PF 100VDCW
ANCI8	0150-2250	CIRCUIT 16 10% PF 500VDCW
ANCI9	0150-2257	CIRCUIT 17 10% PF 500VDCW
ANCI10	0150-0291	CIRCUIT 18 10% PF 500VDCW
ANCI11		NOT ASSIGNED
ANCI12	1901-0040	DIODE SILICON 100MA 100V
ANCI13	1901-0040	DIODE SILICON 100MA 100V
ANCI14	1901-0040	DIODE SILICON 100MA 100V
ANCI15	1901-0040	DIODE SILICON 100MA 100V
ANCI16	1901-0040	DIODE SILICON 100MA 100V
ANCI17	1910-0016	DIODE GERMANIUM 100MA
ANCI18	1910-0016	DIODE GERMANIUM 100MA
ANCI19	1910-0016	DIODE GERMANIUM 100MA
ANCI20	1910-0016	DIODE GERMANIUM 100MA
ANCI21	1910-0016	DIODE GERMANIUM 100MA
ANCI22	1910-0016	DIODE GERMANIUM 100MA
ANCI23	1910-0016	DIODE GERMANIUM 100MA
ANCI24	1910-0016	DIODE GERMANIUM 100MA
ANCI25	1910-0016	DIODE GERMANIUM 100MA
ANCI26	1910-0016	DIODE GERMANIUM 100MA
ANCI27	1910-0016	DIODE GERMANIUM 100MA
ANCI28	1910-0016	DIODE GERMANIUM 100MA
ANCI29	1910-0016	DIODE GERMANIUM 100MA
ANCI30	1910-0016	DIODE GERMANIUM 100MA
ANCI31	1910-0016	DIODE GERMANIUM 100MA
ANCI32	1910-0016	DIODE GERMANIUM 100MA
ANCI33	1910-0016	DIODE GERMANIUM 100MA
ANCI34	1910-0016	DIODE GERMANIUM 100MA
ANCI35	1910-0016	DIODE GERMANIUM 100MA
ANCI36	1910-0016	DIODE GERMANIUM 100MA
ANCI37	1910-0016	DIODE GERMANIUM 100MA
ANCI38	1910-0016	DIODE GERMANIUM 100MA
ANCI39	1910-0016	DIODE GERMANIUM 100MA
ANCI40	1910-0016	DIODE GERMANIUM 100MA
ANCI41	1910-0016	DIODE GERMANIUM 100MA
ANCI42	1910-0016	DIODE GERMANIUM 100MA
ANCI43	1910-0016	DIODE GERMANIUM 100MA
ANCI44	1910-0016	DIODE GERMANIUM 100MA
ANCI45	1910-0016	DIODE GERMANIUM 100MA
ANCI46	1910-0016	DIODE GERMANIUM 100MA
ANCI47	1910-0016	DIODE GERMANIUM 100MA
ANCI48	1910-0016	DIODE GERMANIUM 100MA
ANCI49	1910-0016	DIODE GERMANIUM 100MA
ANCI50	1910-0016	DIODE GERMANIUM 100MA
ANCI51	1910-0016	DIODE GERMANIUM 100MA
ANCI52	1910-0016	DIODE GERMANIUM 100MA
ANCI53	1910-0016	DIODE GERMANIUM 100MA
ANCI54	1910-0016	DIODE GERMANIUM 100MA
ANCI55	1910-0016	DIODE GERMANIUM 100MA
ANCI56	1910-0016	DIODE GERMANIUM 100MA
ANCI57	1910-0016	DIODE GERMANIUM 100MA
ANCI58	1910-0016	DIODE GERMANIUM 100MA
ANCI59	1910-0016	DIODE GERMANIUM 100MA
ANCI60	1910-0016	DIODE GERMANIUM 100MA
ANCI61	1910-0016	DIODE GERMANIUM 100MA
ANCI62	1910-0016	DIODE GERMANIUM 100MA
ANCI63	1910-0016	DIODE GERMANIUM 100MA
ANCI64	1910-0016	DIODE GERMANIUM 100MA
ANCI65	1910-0016	DIODE GERMANIUM 100MA
ANCI66	1910-0016	DIODE GERMANIUM 100MA
ANCI67	1910-0016	DIODE GERMANIUM 100MA
ANCI68	1910-0016	DIODE GERMANIUM 100MA
ANCI69	1910-0016	DIODE GERMANIUM 100MA
ANCI70	1910-0016	DIODE GERMANIUM 100MA
ANCI71	1910-0016	DIODE GERMANIUM 100MA
ANCI72	1910-0016	DIODE GERMANIUM 100MA
ANCI73	1910-0016	DIODE GERMANIUM 100MA
ANCI74	1910-0016	DIODE GERMANIUM 100MA
ANCI75	1910-0016	DIODE GERMANIUM 100MA
ANCI76	1910-0016	DIODE GERMANIUM 100MA
ANCI77	1910-0016	DIODE GERMANIUM 100MA
ANCI78	1910-0016	DIODE GERMANIUM 100MA
ANCI79	1910-0016	DIODE GERMANIUM 100MA
ANCI80	1910-0016	DIODE GERMANIUM 100MA
ANCI81	1910-0016	DIODE GERMANIUM 100MA
ANCI82	1910-0016	DIODE GERMANIUM 100MA
ANCI83	1910-0016	DIODE GERMANIUM 100MA
ANCI84	1910-0016	DIODE GERMANIUM 100MA
ANCI85	1910-0016	DIODE GERMANIUM 100MA
ANCI86	1910-0016	DIODE GERMANIUM 100MA
ANCI87	1910-0016	DIODE GERMANIUM 100MA
ANCI88	1910-0016	DIODE GERMANIUM 100MA
ANCI89	1910-0016	DIODE GERMANIUM 100MA
ANCI90	1910-0016	DIODE GERMANIUM 100MA
ANCI91	1910-0016	DIODE GERMANIUM 100MA
ANCI92	1910-0016	DIODE GERMANIUM 100MA
ANCI93	1910-0016	DIODE GERMANIUM 100MA
ANCI94	1910-0016	DIODE GERMANIUM 100MA
ANCI95	1910-0016	DIODE GERMANIUM 100MA
ANCI96	1910-0016	DIODE GERMANIUM 100MA
ANCI97	1910-0016	DIODE GERMANIUM 100MA
ANCI98	1910-0016	DIODE GERMANIUM 100MA
ANCI99	1910-0016	DIODE GERMANIUM 100MA
ANCI100	1910-0016	DIODE GERMANIUM 100MA

# See introduction to this section for ordering information

Reference Designation	Stock No.	Description #
ANCI56	1970-0025	ELECTRON TUBE
ANCI57	1970-0025	ELECTRON TUBE
ANCI58	1970-0025	ELECTRON TUBE
ANCI59	1970-0025	ELECTRON TUBE
ANCI60	1970-0025	ELECTRON TUBE
ANCI61	1970-0025	ELECTRON TUBE
ANCI62	1970-0025	ELECTRON TUBE
ANCI63	1970-0025	ELECTRON TUBE
ANCI64	1970-0025	ELECTRON TUBE
ANCI65	1970-0025	ELECTRON TUBE
ANCI66	1970-0025	ELECTRON TUBE
ANCI67	1970-0025	ELECTRON TUBE
ANCI68	1970-0025	ELECTRON TUBE
ANCI69	1970-0025	ELECTRON TUBE
ANCI70	1970-0025	ELECTRON TUBE
ANCI71	1970-0025	ELECTRON TUBE
ANCI72	1970-0025	ELECTRON TUBE
ANCI73	1970-0025	ELECTRON TUBE
ANCI74	1970-0025	ELECTRON TUBE
ANCI75	1970-0025	ELECTRON TUBE
ANCI76	1970-0025	ELECTRON TUBE
ANCI77	1970-0025	ELECTRON TUBE
ANCI78	1970-0025	ELECTRON TUBE
ANCI79	1970-0025	ELECTRON TUBE
ANCI80	1970-0025	ELECTRON TUBE
ANCI81	1970-0025	ELECTRON TUBE
ANCI82	1970-0025	ELECTRON TUBE
ANCI83	1970-0025	ELECTRON TUBE
ANCI84	1970-0025	ELECTRON TUBE
ANCI85	1970-0025	ELECTRON TUBE
ANCI86	1970-0025	ELECTRON TUBE
ANCI87	1970-0025	ELECTRON TUBE
ANCI88	1970-0025	ELECTRON TUBE
ANCI89	1970-0025	ELECTRON TUBE
ANCI90	1970-0025	ELECTRON TUBE
ANCI91	1970-0025	ELECTRON TUBE
ANCI92	1970-0025	ELECTRON TUBE
ANCI93	1970-0025	ELECTRON TUBE
ANCI94	1970-0025	ELECTRON TUBE
ANCI95	1970-0025	ELECTRON TUBE
ANCI96	1970-0025	ELECTRON TUBE
ANCI97	1970-0025	ELECTRON TUBE
ANCI98	1970-0025	ELECTRON TUBE
ANCI99	1970-0025	ELECTRON TUBE
ANCI100	1970-0025	ELECTRON TUBE

# See list of abbreviations in introduction to this section

Model 5216A

Table 7-2. A4-05216-6011 Main Board Parts

Section VII  
Manual Changes

Table 7-2. A4-05216-6011 Main Board Parts (Continued)

Reference Designation	Part Stock No.	Description #
1A437	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A438	0683-5125	WIPAD COMP 5600 OHM 5% 1/4W
1A439	0683-5115	WIPAD COMP 510 OHM 5% 1/4W
1A440	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A441	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A442	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A443	0683-4325	WIPAD COMP 4300 OHM 5% 1/4W
1A444	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A445	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A446	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A447	0683-5115	WIPAD COMP 510 OHM 5% 1/4W
1A448	0683-1045	WIPAD COMP 100K OHMS 5% 1/4W
1A449	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A450	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A451	0683-5125	WIPAD COMP 20K OHM 5% 1/4W
1A452	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A453	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A454	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A455	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A456	0683-5125	WIPAD COMP 20K OHM 5% 1/4W
1A457	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A458	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A459	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A460	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A461	0675-1021	WIPAD CARBON 1K OHM 10% 1/4W
1A462	0675-6121	WIPAD COMP 20K OHM 5% 1/4W
1A463	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A464	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A465	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A466	0675-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A467	0675-1021	WIPAD CARBON 1K OHM 10% 1/4W
1A468	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A469	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A470	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A471	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A472	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A473	0675-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A474	0675-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A475	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A476	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A477	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A478	0683-5125	WIPAD COMP 20K OHM 5% 1/4W
1A479	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A480	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A481	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A482	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A483	0675-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A484	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A485	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W
1A486	0683-5125	WIPAD COMP 5100 OHM 5% 1/4W

# See list of abbreviations in Introduction to this section

Reference Designation	Part Stock No.	Description #
1A406	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A407	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A408	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A409	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A410	1854-0009	TRANSISTOR SILICON NPN 2N709
1A411	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A412	1854-0009	TRANSISTOR SILICON NPN 2N709
1A413	1854-0009	TRANSISTOR SILICON NPN 2N709
1A414	1854-0009	TRANSISTOR SILICON NPN 2N709
1A415	1854-0071	TRANSISTOR SILICON NPN 2N3391
1A416	1854-0232	TRANSISTOR SILICON NPN
1A417		NOT ASSIGNED
1A418		NOT ASSIGNED
1A419		NOT ASSIGNED
1A420		NOT ASSIGNED
1A421		NOT ASSIGNED
1A422	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A423	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A424	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A425		NOT ASSIGNED
1A426	0683-2025	WIPAD COMP 2000 OHM 5% 1/4W
1A427		NOT ASSIGNED
1A428	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A429	0683-4325	WIPAD COMP 4300 OHM 5% 1/4W
1A430		NOT ASSIGNED
1A431	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A432	0683-5115	WIPAD COMP 510 OHM 5% 1/4W
1A433	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A434	0683-1025	WIPAD COMP 1000 OHM 5% 1/4W
1A435	0683-1135	WIPAD COMP 11K OHM 5% 1/4W
1A436	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A437	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A438	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A439	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A440	0683-1045	WIPAD COMP 100K OHMS 5% 1/4W
1A441	0683-4715	WIPAD COMP 470 OHM 5% 1/4W
1A442	0683-1535	WIPAD COMP 15K OHM 5% 1/4W
1A443	0683-1535	WIPAD COMP 15K OHM 5% 1/4W
1A444	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A445	0683-1035	WIPAD COMP 10K OHM 5% 1/4W
1A446	0683-4715	WIPAD COMP 470 OHM 5% 1/4W
1A447	0683-2715	WIPAD COMP 27K OHM 5% 1/4W
1A448	0683-4715	WIPAD COMP 470 OHM 5% 1/4W
1A449	0683-4715	WIPAD COMP 470 OHM 5% 1/4W
1A450	0683-4325	WIPAD COMP 4300 OHM 5% 1/4W
1A451	0683-5115	WIPAD COMP 510 OHM 5% 1/4W
1A452	0683-1035	WIPAD COMP 10K OHM 5% 1/4W

# See list of abbreviations in Introduction to this section

**Table 7-4. A3-05216-6006 Oscillator Parts**

Reference Designation	Part No.	Description
A6	05216-0002 05125-2002 05216-0006	POWER SUPPLY ASSY BOARD:BLANK PC HOLDER:POWER SUPPLY
ACR1	0180-2102	CLIP:W ELECT 100 UF +75-10V 25VDCW
ACR2	0180-2101 1400-0040	CLIP:W ELECT 4000 UF +75-10V 15VDCW CLIP:CAPACITOR
ACR3	0180-2103 1400-0042	CLIP:W ELECT 300 UF +75-10V 10VDCW CLIP:CAPACITOR
ACR4	0180-0032	CLIP:W ELECT 10 UF +75-10V 12VDCW
ACR5	0180-0032	CLIP:W ELECT 10 UF +75-10V 12VDCW
ACR6	0180-0032	CLIP:W ELECT 10 UF +75-10V 12VDCW
ACR7	0180-0061	CLIP:W ELECT 100UF +100K-10V 15VDCW
ACR8	0110-0047	CLIP:W MICA 2500 PF 25 500VDCW
ACR9	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR10	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR11	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR12	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR13	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR14	1501-0028	DIODE:ISILICON 400 PIV 0.5 AMP
ACR15	1501-0049	DIODE:ISILICON 50PIV
ACR16	1501-0049	DIODE:ISILICON 50PIV
ACR17	1501-0049	DIODE:ISILICON 50PIV
ACR18	1501-0049	DIODE:ISILICON 50PIV
ACR19	1501-0200	DIODE:ISILICON 100 PIV 1A
ACR20	1501-0200	DIODE:ISILICON 100 PIV 1A
ACR21	1501-0200	DIODE:ISILICON 100 PIV 1A
ACR22	1501-0200	DIODE:ISILICON 100 PIV 1A
ACR23	1502-1036	DIODE:REARADUMN:ISILICON 5.16V
ACR24	1502-1036	DIODE:REARADUMN:ISILICON 5.16V
ACR25	1502-0660	DIODE:REARADUMN:1N,0V 5A
ACR26	1502-1036	DIODE:REARADUMN:ISILICON 5.16V
ACR27	1502-1036	DIODE:REARADUMN:ISILICON 5.16V 5A
ACR28	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR29	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR30	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR31	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR32	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR33	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR34	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR35	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR36	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR37	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR38	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR39	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR40	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR41	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR42	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR43	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR44	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR45	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR46	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR47	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR48	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR49	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR50	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR51	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR52	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR53	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR54	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR55	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR56	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR57	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR58	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR59	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR60	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR61	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR62	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR63	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR64	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR65	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR66	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR67	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR68	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR69	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR70	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR71	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR72	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR73	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR74	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR75	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR76	1502-0671	DIODE:REARADUMN:1N,0V 2A
ACR77	1502-0671	DIODE:REARADUMN:1N,0V 2A


# See introduction to this section for ordering information

Reference Designation	Part No.	Description #
A3	05216-6005	OSCILLATOR ASSY
	09716-2005	MUJAJIBLANK PC
A3C1	0180-0291	CIFXD ELECT 1 OF 101 35VDCW
A3C2	0180-0291	CIFXD ELECT 1 OF 101 35VDCW
A3C3	0180-2201	CIFAD MICA 100 PF 5%
A3C4	0180-2201	CIFAD MICA 51 PF 5%
A3C5	0121-0178	CIVAR CER 15-PC PF
A3C6	0121-0060	CIVAR CER 2-4 PF
A3C7	0180-2201	CIFAD MICA 51 PF 5%
A3C8	0180-2211	CIFAD MICA 510 PF 5% 36VDCW
A3C9	0150-0093	CIFAD CER 0.01 IN 5PC-2ER 100VDCW
A3C10	0180-0945	CIFAD MICA 410 PF 5%
A3L1	9140-0129	CULIFED RT 220 OH
A3Q1	1854-0092	TRANSISTOR SILICON NPN
A3Q2	1854-0009	TRANSISTOR SILICON NPN PNP
A3R1	0683-1015	RIFAD COMP 300 OHM 5% 1/4W
A3R2	0683-3025	RIFAD COMP 3000 OHM 5% 1/4W
A3R3	0683-4125	RIFAD COMP 4500 OHM 5% 1/4W
A3R4	0683-67.5	RIFAD COMP 6700 OHM 5% 1/4W
A3R5	0683-1015	RIFAD COMP 300 OHM 5% 1/4W
A3R6	0683-1025	RIFAD COMP 1000 OHM 5% 1/4W
A3R7	0683-7025	RIFAD COMP 2000 OHM 5% 1/4W
A3R8	0683-1025	RIFAD COMP 1000 OHM 5% 1/4W
A3AY1	1200-0159	CRYSTAL HOLDER
A3Y1	0410-0130	CRYSTAL QUARTZ 10 MHZ

\* See Introduction to this section for ordering information



Figure 7-1. A1 Input Attenuator (Component Locator) (Sheet 1 of 2)






Figure 7-2. A4 Main Board (Schematic) (Sheet 1 of 3)




Figure 7-3. A4 Main Board (Schematic) (Sheet 2 of 3)

Model 5216A




Figure 7-4. A4 Main Board (Schematic) (Sheet 3 of 3)






Figure 7-5. A6 Power Supply (Component Locator) (Sheet 1 of 2)



A6

Figure 7-5. A6 Power Supply (Schematic) (Sheet 2 of 2)



7-16



Figure 7-7. A4 Main Board (Schematic) (Sheet 2 of 3)





Figure 7-8. A4 Main Board (Component Locator)






Figure 7-10. A4 Main Board (Schematic) (Sheet 2 of 3)

Model 5216A






Figure 7-11. A4 Main Board (Schematic) (Sheet 3 of 3)





A3

DS4 DS5 DS6 DS7

SERIES 718

H23

H12


DS3

DS2

DS1

A5

Figure 7-13. A3 10 MHz Oscillator, A5 Decimal Point and Measurement Unit (Schematic) (Sheet 2 of 2)

Section VII  
Manual Changes

# SCHEMATIC DIAGRAMS



## SECTION VIII

### CIRCUIT DIAGRAMS

#### 8-1. INTRODUCTION

8-2. This section includes the following:

a. General Notes for Schematic Diagrams (Figure 8-1).

b. Functional flow diagrams for the gating section of Main Board Assembly A4 (Figures 8-2 through 8-5).

c. Schematic Diagrams and Component Location Illustrations of Model 5216A printed circuit assemblies in the order of their assembly designation (A1 through A6, Figures 8-6 through 8-11). These figures may also include waveforms and voltages. Top view of integrated circuits is shown with pin numbers for identification.

8-3. The Flow Diagrams or any schematic diagram, when unfolded, can be used with any other part of this manual, or with the manual closed.

8-4. DC Voltages are measured with a HP Model 412A DC Voltmeter. Typical voltages are shown.

8-5. Waveforms taken with a HP Model 175A Oscilloscope with the HP 1755A Dual Trace Amplifier plug-in installed. Oscilloscope vertical amplifier bandwidth is at least 20 MHz when used with 10:1 divider probe HP 10001A.

8-6. Shaded areas on the schematic diagrams indicate printed circuit board assemblies. All components within the shaded areas are mounted on the boards.

Figure 8-1. Schematic Diagram Notes





Figure 8-2. Integrated Circuit Diagram

1820-0065(SN7470N)  
J-K FLIP-FLOP

POSITIVE LOGIC

LOW INPUT TO PRESET SETS Q TO LOGICAL 1  
LOW INPUT TO CLEAR SET Q TO LOGICAL 0

TRUTH TABLE


$t_n$	$t_{n+1}$	
J	K	Q
0	0	$Q_n$
0	1	0
1	0	1
1	1	$\overline{Q_n}$

## NOTE:


CLOCK MUST BE AT LOGICAL 0 PRIOR TO THE APPLICATION OF PRESET OR CLEAR FUNCTIONS.

## NOTES:

1.  $J = J_1, J_2, \overline{J}$
2.  $K = K_1, K_2, \overline{K}$
3.  $t_n$  = BIT TIME BEFORE CLOCK PULSE
4.  $t_{n+1}$  = BIT TIME AFTER CLOCK PULSE

1820-0072  
DUAL 2-WIDE 2-INPUT AND-OR-INVERT  
GATES (SN7450N)

POSITIVE LOGIC

 $Y = (AB) + (CD) + X$   
 $X = ABCD$  from SN7460N1820-0075(SN7473N)  
DUAL J-K MASTER-SLAVE FLIP-FLOPTRUTH TABLE  
(EACH FLIP-FLOP)

$t_n$	$t_{n+1}$	
J	K	Q
0	0	$Q_n$
0	1	0
1	0	1
1	1	$\overline{Q_n}$

## NOTES

1.  $t_n$  = BIT TIME BEFORE CLOCK PULSE
2.  $t_{n+1}$  = BIT TIME AFTER CLOCK PULSE
3. POSITIVE LOGIC:  
LOW INPUT TO CLEAR SETS Q TO LOGICAL 0 REGARDLESS OF CLOCK STATE

Figure 8-2. Integrated Circuit Diagram (Continued)






Figure 8-2. Integrated Circuit Diagram (Continued)





**Figure 8-3. Flow Diagram for Frequency Measurements**





Figure 8-4. Flow Diagram for  
Period Measurements



**Figure 8-5. Flow Diagram for Ratio Measurements**








Figure 8-6. Flow Diagram for  
Time Interval Measurements





A2



NOTES

- 1. REFERENCE DESIGNATIONS WITHIN THIS ASSEMBLY ARE ABBREVIATED. ADD ASSEMBLY NUMBER TO ABBREVIATION FOR COMPLETE DESCRIPTION.
- 2. UNLESS OTHERWISE INDICATED: RESISTANCE IN OHMS; CAPACITANCE IN PICOFARADS;

REFERENCE DESIGNATIONS

A1	A2
	C1-11
	CR3
	J1,2
	Q1-11
	R1-27
R10	

DELETED CR1,2

COPYRIGHT 1967 BY HEWLETT-PACKARD COMPANY  
CSP-6-D-148C

Figure 8-8. A2 Input Amplifier  
8-17







Figure 8-9. A3 10 MHz Oscillator  
A5 Decimal Point and Measurement Unit




① .5V/cm; 1  $\mu$ sec/cm




② .2V/cm; .5  $\mu$ sec/cm




③ .2V/cm; .5  $\mu$ sec/cm




④ .5V/cm; 5  $\mu$ sec/cm



⑤ .5V/cm; 5.0  $\mu$ sec/cm




⑥ .5V/cm; 50  $\mu$ sec/cm




⑦ .5V/cm; .2 msec/cm



⑧ .5V/cm; 2.0 msec/cm




⑨ .5V/cm; .02 sec/cm



⑩ .5V/cm; 0.1 sec/cm




⑪ .2V/cm; .5  $\mu$ sec/cm




⑫ .2V/cm; .5  $\mu$ sec/cm




⑬ .2V/cm; 20  $\mu$ sec/cm




⑭ .2V/cm; 50  $\mu$ sec/cm




⑮ .2V/cm; .2 msec/cm




⑯ .2V/cm; 2 msec/cm




⑰ .2V/cm; 10 msec/cm




⑱ .2V/cm; .1 sec/cm







① .5V/cm; 1  $\mu$ sec/cm




② .2V/cm; .5  $\mu$ sec/cm




③ .2V/cm; .5  $\mu$ sec/cm




④ .5V/cm; .5  $\mu$ sec/cm




⑤ .5V/cm; 5.0  $\mu$ sec/cm



⑥ .5V/cm; 50  $\mu$ sec/cm



⑦ .5V/cm; 2 msec/cm




⑧ .5V/cm; 2.0 msec/cm



⑨ .5V/cm; .02 sec/cm



⑩ .5V/cm; 0.1 sec/cm




⑪ .2V/cm; .5  $\mu$ sec/cm




⑫ .2V/cm; .5  $\mu$ sec/cm




⑬ .2V/cm; 20  $\mu$ sec/cm




⑭ .2V/cm; 50  $\mu$ sec/cm




⑮ .2V/cm; .2 msec/cm





⑯ .2V/cm; 2 msec/cm




⑰ .2V/cm; 10 msec/cm




⑱ .2V/cm; .1 sec/cm









① .5V/cm; 1  $\mu$ sec/cm




② .2V/cm; .5  $\mu$ sec/cm




③ .2V/cm; .5  $\mu$ sec/cm




④ .5V/cm; .5  $\mu$ sec/cm




⑤ .5V/cm; 5.0  $\mu$ sec/cm




⑥ .5V/cm; 50  $\mu$ sec/cm




⑦ .5V/cm; .2 msec/cm




⑧ .5V/cm; 2.0 msec/cm




⑨ .5V/cm; .02 sec/cm




⑩ .5V/cm; 0.1 sec/cm




⑪ .2V/cm; .5  $\mu$ sec/cm




⑫ .2V/cm; .5  $\mu$ sec/cm



⑬ .2V/cm; 20  $\mu$ sec/cm




⑭ .2V/cm; 50  $\mu$ sec/cm




⑮ .2V/cm; .2 msec/cm





⑯ .2V/cm; 2 msec/cm




⑰ .2V/cm; 10 msec/cm




⑱ .2V/cm; .1 sec/cm





02430-3



- NOTES
1. REFERENCE DESIGNATIONS WITHIN THIS ASSEMBLY ARE ABBREVIATED. ADD ASSEMBLY NUMBER TO ABBREVIATION FOR COMPLETE DESCRIPTION.
  2. UNLESS OTHERWISE INDICATED:  
RESISTANCE IN OHMS;  
CAPACITANCE IN PICOFARADS;  
INDUCTANCE IN MICROHENRIES
  3. ASTERISK(\*) INDICATES SELECTED COMPONENT, AVERAGE VALUES SHOWN
  4. FOR 230V OPERATION  
SWITCH S4 TO 230V POSITION  
CHANGE F1 TO .15A (SB)

REFERENCE DESIGNATIONS

NO PREFIX	A6
C2	C1-9
F1	CR1-19
J7	J1
L1,2	
P7	
Q1	Q1-7
S1,4	R1-12
T1	RT1
W1	

Figure 8-11. A6 Power Supply  
8-27

# MANUAL CHANGES

# HEWLETT PACKARD

## MANUAL CHANGES

MANUAL DESCRIPTION	
INSTRUMENT:	5216A Electronic Counter
SERIAL PREFIX:	1040A
DATE PRINTED:	AUG 1971
HP PART NO:	05216-9006

**CHANGE DATE:** October 11, 1973

(This change supersedes all earlier dated changes)

- Make all changes listed as ERRATA.
- Check the following table for your instrument's serial prefix or serial number and make listed change(s) to manual.

IF YOUR INSTRUMENT HAS SERIAL PREFIX OR SERIAL NUMBER	MAKE THE FOLLOWING CHANGES TO YOUR MANUAL	IF YOUR INSTRUMENT HAS SERIAL PREFIX OR SERIAL NUMBER	MAKE THE FOLLOWING CHANGES TO YOUR MANUAL

► **NEW OR REVISED ITEM**

**ERRATA**

Page 6-3, Table 6-1:

Change A41C1, 2A, 2B, 3A/B, 4A/B from 1820-0412 to 1820-0413.

Change 1200-0415 to 1200-0474.

► Change A41C4B from 1820-0413 to 1820-0412.

This change supersedes other applicable data.

Page 6-6, Table 6-1:

Change W1 from 8120-1348 to 8120-1378.

Page 6-8, Table 6-2:

Change 1200-0415 to 1200-0474.

Add 0180-1943 C: FXD ALUM 1000UF +75-10% 25VDCW.

Page 6-9, Table 6-2:

Change 1820-0412 to 1820-0413 in both HP Part No. and Mfr Part No. columns.

► Page 7-5, Table 7-2:

Change A41C4B from 1820-0413 to 1820-0412.

Page 8-21, Figure 8-10:

Change IC Part Nos. as on Page 6-3.

Page 8-27, Figure 8-11:

Change A6C3 to 1000 UF.