

Programiranje HMC702LP6C za 32.000MHz TCXO HMC586+368					28.02.2014
Register	RESET: privzeta vsebina	CW 10.3681GHz	AutoSweep ~9...15GHz	TrigSwpUp ~9...15GHz	SingleStep ~9...15GHz
00	581504	0:000003	<<<<<<<<<	<<<<<<<<	<<<<<<<<
01	00FE9B				
02	0003C3				
03	008001				
04	000000				
05	000006	0:000007	<<<<<<<<	<<<<<<<<	<<<<<<<<
06	000002				
07	000210				
08	020400				
09	000000				
0A	000304				
0B	000000				
0C	000100				
0D	000020				
0E	000000				
0F	0000c8	0:000051	0:000049	<<<<<<<<	<<<<<<<<
10	000000	0:003333	<<<<<<<<	<<<<<<<<	<<<<<<<<
11	000000	0:DEADBE	<<<<<<<<	<<<<<<<<	<<<<<<<<
12	030E82	0:030F82	<<<<<<<<	<<<<<<<<	<<<<<<<<
13	000000				
14	000000		1:00000A 2:00000E	1:0000A2	1:000062
15	000800				0:600000
16	000800		0:060000	<<<<<<<<	0:000080
17	000800		0:008000	<<<<<<<<	<<<<<<<<
18	0000A0				
19	00000F				
1A	001040				
1B	000000		0:000488	<<<<<<<<	<<<<<<<<
1C	000020				
1D	000000				
1E	000000				
1F	000000				
20	000020				
21	00000c				
22	000000				